
Step 1 - How to Install the Barracuda Load Balancer ADC Appliance

<https://campus.barracuda.com/doc/19333379/>

Deployment Options

Before installation, determine the best type of deployment for your Barracuda Load Balancer ADC; refer to the [Deployment](#) section for a list of options.

Verify Equipment

Verify you have the necessary equipment:

- Barracuda Load Balancer ADC
- AC power cord
- Ethernet cables
- Mounting rails and screws
- Monitor and keyboard (recommended)

Connect to the Network

1. Secure the Barracuda Load Balancer ADC in your environment.
2. Connect the Barracuda Load Balancer ADC to your network:
 - On the front of the device, connect the ports based on your deployment
 - Connect an Ethernet cable from the management port (either labeled MGMT or unlabeled on the back of the device) to the network switch for your management network.
3. Connect the following to your Barracuda Load Balancer ADC:
 - Power cord; AC input voltage range is 100-200 volts at 50/60 Hz
 - Monitor and keyboard
4. Power on the device.

Configure the Management IP Address

Once fully booted, the login prompt appears on your monitor. To configure the management IP address:

1. At the barracuda login prompt, log in using **admin/admin**.

Barracuda recommends changing the administrator password. On the console, you can change the admin password from the **System** menu.

2. Go to **TCP/IP Configuration**, and in the right pane, configure the addresses as appropriate for your network, including :
 - Management IP Address /Netmask
 - Gateway Address
 - Management VLAN ID (Optional)
 - Primary/Secondary DNS Servers
 - Proxy Server Configuration (Optional)
3. Select **Save** to save your changes, and then select **Exit** .

Continue with [Step 2 - How to Configure the Barracuda Load Balancer ADC](#).

© Barracuda Networks Inc., 2019 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.