

## System Log Messages

<https://campus.barracuda.com/doc/39818198/>

The following is the list of system log messages, which includes the following:

- **Log Category** - The Severity Level of the log.
- **Log ID** - The Event ID of the log.
- **Log Message** - Description about the log.

Log Category	Log ID	Log Message
	8	Unknown Error
	110	Network Unreachable
	111	Connection Refused
<b>Data Path Monitoring (STM)</b>		
	1001	System Out of Memory
	1002	System WAC Version
LOG_NOTICE	1003	Mem Start: SCB <start-address>, Low <start-address>, High <start-address>
	1004-8	System Process Related
	1009	System Upgrade related
	1010	Date Setting related
	1011	Time Zone related
	1012	System Shutdown
LOG_CRIT	1013	System startup failed at initializing: <stage>. Switching to maintenance mode
LOG_CRIT	1014	Shutting down all services
LOG_NOTICE	1014	Shutting down services completed
LOG_NOTICE	1015	Restarting services
LOG_NOTICE	1015	Restarting services completed
	1016	Core Dump
	1017	Process Start
	1018	Booting related
LOG_NOTICE	1019 - 1028	Activate: Default boot image set to <Image Name> System Related
LOG_EMERG	1105	<Process> is not present
LOG_NOTICE	1111	Process mon /proc error ret =<retcode> comm=<commandid> pid=<process-id>

LOG_ALERT	1119	(System is getting real hot) or (Possible overheating at device <device-name> temp reading=<temp in 'C>)
LOG_ALERT	1125	SBC PII temp overshoot.
LOG_ALERT	1126	System highest temp has reached = <External temp 'C> <Internal Temp in 'C>
LOG_ALERT	1128	In Fan Group <Group ID> Fan <Fan ID> is Running at <Current Value> rps which is less than expected <default value>
LOG_NOTICE	1130	HW: Changing FAN speed <Old Value> -> <New Value> TempReadings (<Max internal 'C> <Max External temp in 'C>)]
LOG_NOTICE	1203	SBC FAN <fan-name> detected rpm = <rpm value>
<b>System RPCs</b>		
	2001-12	System RPCs Related
<b>Threshold Controlled (THRSHLD)</b>		
LOG_ALERT	50001	Threshold Level crossed.
LOG_ALERT	50002	Threshold Level crossed on a service.
LOG_ALERT	50003	System critical temp has reached.
LOG_ALERT	50004	System highest temp has reached.
LOG_ALERT	50005	One of the CPU/System fans is dead.
LOG_ALERT	50007	Firmware storage exceeds 85%.
LOG_ALERT	50008	Mail storage exceeds 85%.
LOG_ALERT	50009	Log storage exceeds 85%.
LOG_ALERT	50010	One of the RAID arrays is degrading.
<b>SERVICE</b>		
LOG_NOTICE	14001	New Service (ID 0x<vip-context>) Created at <IP Address>:<Port>
LOG_ERROR	14001	Failed to Create Service at <IP Address>:<Port>
LOG_NOTICE	14002	Service Started <IP Address>:<Port>
LOG_ERROR	14003	Failed to Delete Service (ID 0x%08x) at <IP Address>:<Port>
LOG_ERROR	14004	Failed to Create Rule at <IP Address>:<Port>
LOG_NOTICE	14004	New Rule (ID 0x<rule-context>) Created at <IP Address>:<Port> for ID 0x<vip-context>
LOG_NOTICE	14005	Committed: URL [<URL Key>] Header [<Header Key>]
LOG_ERROR	14006	Deleted Rule (ID <vapp-context> at <IP:Port> URL [<URL Key>] Header [<Header Key>]
LOG_ERROR	14007	Failed to Create Service at <IP Address>:<Port>
LOG_NOTICE	14007	New Vapp (ID 0x<vapp-context>) Created at <IP Address>:<Port> for ID 0x<vip-context>
LOG_NOTICE	14008	Failed to commit Application: Domain [<Application Rule Domain>] URL [<Application Rule URL>]

LOG_ERROR	14009	Failed to Delete Vapp (ID 0x<vapp-context>) at <IP Address>:<Port> Domain [<Application Rule Domain>] URL [<Application Rule URL>]
<b>Config Agent (CONFIG)</b>		
LOG_ERROR	12001	Local GATEWAY_NAME not found
LOG_ERROR	12001	Digest failed
LOG_ERROR	12001	No Monitoring Dispatcher found
LOG_ERROR	12001	To execute this operation, peer node should be non-operational
LOG_ERROR	12001	Configuring Secure Traffic Manager Succeeded
LOG_ERROR	12001	Failed to resolve type of clear stats
LOG_ERROR	12002	Duplicate parameter
LOG_ERROR	12002	Target doesn't exist
LOG_ERROR	12002	Deleting RuleBackup
LOG_ERROR	12002	RuleBackup delete succeeded
LOG_ERROR	12002	Deleting ServerBackup
LOG_ERROR	12002	ServerBackup delete succeeded
LOG_ERROR	12002	Unable to delete ServerBackup
LOG_ERROR	12002	Deleting Server
LOG_ERROR	12002	Server delete succeeded
LOG_ERROR	12002	Unable to delete Server
LOG_ERROR	12002	Deleting application key
LOG_ERROR	12002	Application key delete succeeded
LOG_ERROR	12002	Unable to delete application key
LOG_ERROR	12002	Deleting QOS class
LOG_ERROR	12002	QOS class delete succeeded
LOG_ERROR	12002	Unable to delete QOS class
LOG_ERROR	12002	Deleting Service
LOG_ERROR	12002	Service delete succeeded
LOG_ERROR	12002	Unable to delete Service
LOG_ERROR	12002	Deleting ACL
LOG_ERROR	12002	ACL delete succeeded
LOG_ERROR	12002	Unable to delete ACL
LOG_ERROR	12002	Deleting NAT entry
LOG_ERROR	12002	NAT entry delete succeeded
LOG_ERROR	12002	Unable to delete NAT entry
LOG_ERROR	12002	Deleting ARP entry
LOG_ERROR	12002	ARP entry delete succeeded

LOG_ERROR	12002	Duplicate route
LOG_ERROR	12002	Deleting route
LOG_ERROR	12002	Route delete succeeded
LOG_ERROR	12002	Unable to delete route
LOG_ERROR	12002	Deleting Interface
LOG_ERROR	12002	Interface delete succeeded
LOG_ERROR	12002	Unable to delete Interface
LOG_ERROR	12002	Deleting VirtualHost
LOG_ERROR	12002	VirtualHost delete succeeded
LOG_ERROR	12002	Unable to delete VirtualHost
LOG_ERROR	12002	Adding VirtualHost
LOG_ERROR	12002	VirtualHost add succeeded
LOG_ERROR	12002	Unable to add VirtualHost
LOG_ERROR	12002	Adding Interface
LOG_ERROR	12002	Interface add succeeded
LOG_ERROR	12002	Unable to add Interface
LOG_ERROR	12002	Interface modify succeeded
LOG_ERROR	12002	Unable to modify Interface
LOG_ERROR	12002	Adding ARP entry
LOG_ERROR	12002	ARP entry add succeeded
LOG_ERROR	12002	Unable to add ARP entry
LOG_ERROR	12002	ARP entry modify succeeded
LOG_ERROR	12002	Unable to modify ARP entry
LOG_ERROR	12002	Adding Route
LOG_ERROR	12002	Route add succeeded
LOG_ERROR	12002	Unable to add Route
LOG_ERROR	12002	Gateway is not directly reachable on any interface
LOG_CRIT	12003	Failed to retrieve initial groups
LOG_ERROR	12004	Can't store rule ID
LOG_ERROR	12005	Can't get "NEXTSAPID": missing "SAPID" or error retrieving "SAPID"
LOG_ERROR	12007	\$NC_INSTALL_ROOT not set
LOG_ERROR	12007	Target doesn't exist
LOG_ERROR	12007	Failed to create server
LOG_ERROR	12007	SetServerConnAttr failed
LOG_ERROR	12007	SetServerRedirectAttr failed
LOG_ERROR	12007	SetServerOutOfBandMonitorAttr failed

LOG_ERROR	12007	SetServerMonitorAttr failed
LOG_ERROR	12007	SetServerLBAttr failed
LOG_ERROR	12007	StartServer failed
LOG_ERROR	12007	SetServerSSLServicePolicy failed
LOG_ERROR	12007	SetServerSSLServiceOn failed
LOG_ERROR	12007	SetServerSSLServiceOff failed
LOG_ERROR	12007	ActiveServerOutOfBandMonitorAttr failed
LOG_ERROR	12007	Failed to delete server
LOG_ERROR	12007	Failed to reset Server IP, Port or VLAN
LOG_ERROR	12007	Failed to look up server
LOG_ERROR	12007	SetServerTcpMonitorAttr failed
LOG_ERROR	12007	EnableServer failed
LOG_ERROR	12007	DisableServer failed
LOG_ERROR	12007	ActiveServerOutOfBandMonitorAttr failed
LOG_ERROR	12008	Duplicate server
LOG_ERROR	12008	Attaching server
LOG_ERROR	12008	Attaching server succeeded
LOG_ERROR	12008	Failed to look up back-end server
LOG_ERROR	12008	Detaching server
LOG_ERROR	12008	Detaching server succeeded
LOG_ERROR	12009	OUT OF MEMORY !!! Asserting...
LOG_ERROR	12009	Error in reading ReadXmlFileIntoString
LOG_ERROR	12009	sapIndex.AddFromXMLStr (... , SAP::nsap) failed
LOG_ERROR	12009	Could not find mgmt container
LOG_ERROR	12009	Could not find ports/ethernet container
LOG_ERROR	12009	Could not find hardware container
LOG_ERROR	12009	Could not find box container
LOG_ERROR	12009	Could not find linux interface
LOG_ERROR	12009	Could get local box path
LOG_ERROR	12009	AddSAP for box2SAP failed
LOG_ERROR	12009	RecurAddChldOfAggSAP for box2 failed
LOG_ERROR	12009	SetBoxParametersFromOrgTree failed (box2) !
LOG_ERROR	12009	SetBoxName failed (box2) !
LOG_ERROR	12009	SetBoxParametersFromOrgTree failed !
LOG_ERROR	12009	In SetBoxParametersFromOrgTree. Invalid path specified
LOG_ERROR	12009	Could not find Linux interface

LOG_ERROR	12009	There should have been 3 physical interfaces.
LOG_ERROR	12009	SetParameterValuesUnderPath failed !
LOG_ERROR	12009	in SetBoxParametersFromOrgTree. UpdateDefaultRoute failed !
LOG_ERROR	12009	In GetClearConfTree. SetInitValuesForCC failed !
LOG_ERROR	12009	In UpdateDefaultRoute. Should have matched only one route !
LOG_ERROR	12009	In UpdateDefaultRoute. tmpIdx.GetAggSAP failed !
LOG_ERROR	12009	In UpdateDefaultRoute. sapIndex.GetParamSAP failed !
LOG_ERROR	12009	In UpdateDefaultRoute. tmpIdx.GetParamSAP failed !
LOG_ERROR	12009	In UpdateDefaultRoute. tmpIdx.ModifySAP failed !
LOG_ERROR	12009	In GetMD5HashForFile. CheckIfValidFileToRetrieve failed
LOG_ERROR	12009	GetPathForUser failed !
LOG_ERROR	12009	in PutSAPTree. GetHomeDirForUser failed !
LOG_ERROR	12009	In PutSAPTree. Invalid path specified !
LOG_ERROR	12009	In PutSAPTree. Path not found in tmp sapIndex
LOG_ERROR	12009	Error. AddFromXMLStr failed !
LOG_ERROR	12009	in PutSAPTree. Invalid node in treediff result
LOG_ERROR	12009	in PutSAPTree. No acl perm
LOG_ERROR	12009	in PutSAPTree.ModifySAP failed
LOG_ERROR	12009	in PutSAPTree. Trying to modify a read-only node
LOG_ERROR	12009	Cannot modify a read-only node
LOG_ERROR	12009	Couldn't read old bind value
LOG_ERROR	12009	in PutSAPTree.ModifySAP failed
LOG_ERROR	12009	Can't replace the root / (session.cc)in PutSAPTree. GetFatherPath failed
LOG_ERROR	12009	in PutSAPTree.AddChildSAP failed
LOG_ERROR	12009	Can't replace the root /
LOG_ERROR	12009	in PutSAPTree.DeleteSAPTree failed
LOG_ERROR	12009	Error invalid operation type
LOG_ERROR	12009	PutRootSAPTree failed in GetAggSAP
LOG_ERROR	12009	No path provided
LOG_ERROR	12009	Failed due to insufficient user permission
LOG_ERROR	12009	Internal error while adding a child node!
LOG_ERROR	12009	Internal error: while parsing query!
LOG_ERROR	12009	No Parameter found for querying
LOG_ERROR	12009	Parameter must be specified in a Container.
LOG_ERROR	12009	ERROR ! No column names specified!
LOG_ERROR	12009	Invalid or non existent home directory found !

LOG_ERROR	12009	CheckPermForInterNodes failed
LOG_ERROR	12009	GetPathForUser failed
LOG_ERROR	12009	Context doesn't exist !
LOG_ERROR	12009	In CheckPermForQuery. AcIMatchAuth failed!
LOG_ERROR	12009	in CheckPermForInterNodes. GetHomeDirForUser failed
LOG_ERROR	12009	In CheckPermForInterNodes. AcIMatchAuth failed!
LOG_ERROR	12009	in CheckPermAndSet. GetPermissionForUser failed
LOG_ERROR	12009	Non-existing path corresponding to global parameters
LOG_ERROR	12009	Error in SystemBackUp. failed to acquire mutex.
LOG_ERROR	12009	in RecurAddAcl. GetRelativePath failed !
LOG_ERROR	12009	Session::GetCommandsForUser.
LOG_ERROR	12009	Empty peer gateway key
LOG_ERROR	12009	Setting of peer gateway key failed
LOG_ERROR	12009	in CheckReadPermOnParent. GetFatherPath failed
LOG_ERROR	12009	in GetAbsBindPath. GetHomeDirForUser failed !
LOG_ERROR	12009	GetWacBoxVersion failed !
LOG_ERROR	12009	GetInterfaceAddress failed !
LOG_ERROR	12010	Failed to set SetVipSSLEphemeralKey
LOG_ERROR	12010	Policy is bound to more than one QOS class
LOG_ERROR	12010	Failed to set " SERVICE_APP_PROTOCOL "
LOG_ERROR	12010	Failed to set " SERVICE_APP_PROTOCOL " on
LOG_ERROR	12010	Adding qos class
LOG_ERROR	12010	Setting qos class
LOG_ERROR	12010	Unsetting qos class
LOG_ERROR	12010	Duplicate application
LOG_ERROR	12010	Failed to find back-end server in server list
LOG_ERROR	12010	Failed to look up Secure Traffic Manager object
LOG_ERROR	12011	Couldn't add paramSAP, name:
LOG_ERROR	12013	Failed to allocate space for integer argument
LOG_ERROR	12013	Failed to allocate space for float argument
LOG_ERROR	12013	Failed to allocate space for long long argument
LOG_ERROR	12013	Failed to allocate space for char string argument
LOG_ERROR	12014	Unable to get import/export handle
LOG_ERROR	12014	Unable to set error handle
LOG_ERROR	12014	Couldn't get file handle
LOG_ERROR	12014	Set file handle failed

LOG_ERROR	12014	Couldn't ready curl for upload
LOG_ERROR	12014	Couldn't set file size
LOG_ERROR	12014	Unsupported method
LOG_ERROR	12014	Couldn't set target
LOG_ERROR	12015	SSL Version 3 enabled
LOG_ERROR	12015	TLS enabled
LOG_ERROR	12015	No key/cert bindings found
LOG_ERROR	12015	Attempt to use unsupported key type
LOG_ERROR	12015	Unable to extract certificate
LOG_ERROR	12015	Unable to extract issuer certificate
LOG_ERROR	12015	Unable to extract key
LOG_ERROR	12015	Unable to extract exchange key
LOG_ERROR	12015	Error extracting trusted certificate
LOG_ERROR	12018	Internal Error
LOG_ERROR	12018	Invalid Path Specified
LOG_ERROR	12019	Unable to allocate memory
LOG_ERROR	12021	in ParamCmp. Cant modify node attributes
LOG_ERROR	12021	Incorrect permissions given to root role
LOG_ERROR	12021	Cannot modify ACL for root node
LOG_ERROR	12021	Cannot give write permissions for a read-only node.
LOG_ERROR	12021	in TreeDiff::GetDiff. Invalid path passed !
LOG_ERROR	12021	in AggCmp. Cant modify node attributes
LOG_ERROR	12021	managementSystemErrorMessage
LOG_ERROR	12021	in GetDiff. Retrieved inv. node
LOG_ERROR	12021	in GetDiff.AddInterNodes fail!
LOG_ERROR	12021	in GetDiff. inv. node
LOG_ERROR	12021	In GetDiff. invalid return from SAPCmp!
LOG_ERROR	12024	Backup rule group cannot be the same as the primary rule group
LOG_ERROR	12027	Value for " CACHE_SVC_MAX_OBJECT_SIZE " too large
LOG_ERROR	12028	Invalid value for " NET_INTERFACE_OPERATION_STATUS " . Using default
LOG_ERROR	12028	Unable to set media-mode
LOG_ERROR	12029	Failed to create HTTP monitor
LOG_ERROR	12030	Failed to look up primary server
LOG_ERROR	12030	Failed to look up backup server



LOG_ERROR	12031	Failed to add route on <mgmt-port> due to: netmask doesn't match route address
LOG_ERROR	12031	Netmask doesn't match route address
LOG_ERROR	12031	Modify Route: Unsupported operation
LOG_ERROR	12032	Failed to add route
LOG_ERROR	12033	Unsupported operation
LOG_ERROR	12038	Unexpected REN_AGG
LOG_NOTICE	12040	Processing messages in the list
LOG_ERROR	12041	Connection NULL in NC_RemoteCaller::getResponseHandle
LOG_ERROR	12049	Can not parse cluster info
LOG_ERROR	12049	Can not send message to heartbeat. Heartbeat Socket is NULL
LOG_CRIT	12049	Peer IP Address is NULL. Exiting
LOG_CRIT	12049	\$NC_HEARTBEAT_DIR not set. Exiting
LOG_NOTICE	12049	Processing messages in the list failed. Ignoring the error
LOG_NOTICE	12049	Starting main message processing loop
LOG_NOTICE	12049	Initiating login to Local SAPD after updating configuration
LOG_NOTICE	12049	Getting Cluster Information after updating configuration
LOG_NOTICE	12049	Configuration database versions match. Setting contactPeer flag to true
LOG_NOTICE	12049	Configuration database versions mismatch. Setting contactPeer flag to false.
LOG_CRIT	12049	Can not relogin to SAPD. Exiting
LOG_CRIT	12049	Going to maintenance mode
LOG_CRIT	12049	\$NC_INSTALL_ROOT not set.
LOG_CRIT	12049	Failed to create cluster key. This will shutdown communication with the peer-node
LOG_CRIT	12049	Failed to create peer-gateway key. This will shutdown communication with the peer-node
LOG_CRIT	12049	Failed to create encryption keys for peer-peer communication
LOG_ERROR	12050	Heartbeat Client closing socket
LOG_ERROR	12050	Heartbeat Client can not open socket
LOG_ERROR	12050	Heartbeat Client can not read message from Heartbeat Server
LOG_ERROR	12050	Can not send message to Heartbeat
LOG_ERROR	12051	The account has been disabled. Please contact your admin
LOG_ERROR	12051	Only one more day left to expire your password. Please change your password now
LOG_ERROR	12051	Your password is about to expire. Please change your password
LOG_ERROR	12053	Failed to initialize signal handlers

LOG_ERROR	12053	Failed to digest initial configuration
LOG_ERROR	12053	Failed to bind transResponse socket on 127.0.0.1
LOG_ERROR	12053	Exec for switchtomaint.sh failed
LOG_ERROR	12053	Termination requested by the signal handler
LOG_ERROR	12054	GetCmdGrpXML failed
LOG_ERROR	12054	sapIndex.AddFromXMLStr(..., \"nc:ncRoot\") failed
LOG_ERROR	12054	Usage: sap_initdb xmlFile
LOG_ERROR	12054	Failed to initialize the sessions DB
LOG_ERROR	12054	Failed to initialize SAP DB
LOG_ERROR	12054	Failed to set System Configuration Timestamp to 0
LOG_ERROR	12054	Failed to set Configuration Tree Timestamp to 0
LOG_ERROR	12057	Can't store vhid
LOG_ERROR	12057	Updating virtual host id is not supported
LOG_ERROR	12058	Sysmon Client closing socket
LOG_ERROR	12058	Sysmon Client can not open socket
LOG_ERROR	12058	Sysmon Client: cannot bind to Socket
LOG_ERROR	12058	Sysmon Client can not read message
LOG_ERROR	12058	Can not allocate memory for sysmon event message
LOG_ERROR	12058	Can not allocate memory for sapd event message
LOG_ERROR	12058	Unknown message received from Sysmon
LOG_ERROR	12058	Unknown message to sysmon
LOG_ERROR	12066	Socket::WritePktToSocket - sockfd == -1
LOG_ERROR	12067	Failed to look up associated application
LOG_ERROR	12067	Adding Application
LOG_ERROR	12067	Duplicate app key
LOG_ERROR	12067	No app keys
LOG_ERROR	12067	Failed find back-end server in server list
LOG_ERROR	12067	No such object
LOG_ERROR	12068	No rules
LOG_ERROR	12068	Failed find back-end server in server list
LOG_ERROR	12070	Invalid value specified for IPS_COOKIE_MODE),
LOG_ERROR	12073	Duplicate User Realm name: "+authUserRealmName
LOG_ERROR	12073	Failed to write userRealm Name "+authUserRealmName
LOG_ERROR	12073	User Realm name doesn't exist
LOG_ERROR	12073	Failed to delete User Realm name "+ realms_.GetRealmName
LOG_ERROR	12073	Failed to delete User Realm conf file "+ realms_.GetRealmName

LOG_ERROR	12074	InterfaceDependantKey
LOG_ERROR	12081	Finalize succeeded!
LOG_ERROR	12083	Failed to look up Secure Traffic Manager object
LOG_ERROR	12083	No such object
LOG_ERROR	12085	Invalid parameter length " IPS_WEBGATE_START_URL "
LOG_ERROR	12085	Invalid parameter length IPS_WEBGATE_REDIRECT_URL
LOG_ERROR	12085	Invalid parameter length " IPS_WEBGATE_COOKIE_NAME
LOG_ERROR	12085	Invalid parameter length " IPS_WEBGATE_COOKIE_VALUE
LOG_ERROR	12085	Invalid parameter length " IPS_WEBGATE_COOKIE_EXPIRES
LOG_ERROR	12085	Invalid parameter length " IPS_WEBGATE_COOKIE_PATH
LOG_ERROR	12085	Invalid parameter length " IPS_WEBGATE_COOKIE_DOMAIN
LOG_ERROR	12085	Invalid parameter value " IPS_WEBGATE_COOKIE_SECURE
LOG_ERROR	12088	Invalid parameter value <IPS_REDIRECT_STATUS>
LOG_ERROR	12088	Invalid parameter value <IPS_REWRITE_STATUS>
LOG_ERROR	12089	Invalid parameter value <IPS_BLOCK_SOAP_REQ >
LOG_ERROR	12090	Error in ReconfigureSubPolicies mismatch in number of sub-policies
LOG_ERROR	12100	Invalid sessionid specified for StartPktTrace
LOG_ERROR	12100	Invalid port specified for Packet dump
LOG_ERROR	12100	Invalid sessionid specified for StartPktTrace
LOG_ERROR	12102	Maximum allowed groups exceeded
LOG_ERROR	12109	Invalid value for < ACL_PROTOCOL > (Must be an integer between 0 and 255, inclusive)
LOG_ERROR	12109	Unsupported operation ACL
LOG_ERROR	12197	Failed to start Session Recording
LOG_ERROR	12197	Failed to stop Session Recording
<b>Caching (CACHE)</b>		
LOG_NOTICE	6001	System Low on Memory: Adjusting Cache Parameters - Current Max:<Max Size>, High:<High Water Mark>, Safe<Safe Water Mark>
LOG_NOTICE	6001	System Low on Memory: Adjusting Cache Parameters - New Max:<Max Size>, High:<High Water Mark>, Safe<Safe Water Mark>
LOG_NOTICE	6002	Cache Purged
LOG_NOTICE	6003	Cache purge failed: instance <Count>, thid <Thread ID>, table <Table ID>, target <Size>, collected <Freed Size>
<b>Load Balance (LB)</b>		
LOG_ALERT	7005	Server <IP Address>:<Port> is enabled
LOG_ALERT	7006	Server <IP Address>:<Port> is disabled. New mode <Operational Mode>

LOG_NOTICE	7007	Server <IP Address>:<Port> is created
LOG_ALERT	7008	Server <IP Address>:<Port> is deleted
LOG_ALERT	7012	Server <IP Address>:<Port> is enabled by configuration.
LOG_ALERT	7013	Server <IP Address>:<Port> is disabled by configuration.
<b>Access Logs (WEBLOG)</b>		
LOG_WARN	9001	Configurations for start or stop time *MAY* not be proper.
LOG_ERROR	9003	Error: Unable to establish control connection.
LOG_ERROR	9004	Error: Unable to establish data connection
LOG_ERROR	9005	Error: Unable to establish SSL control connection
LOG_ERROR	9006	Error: Unable to authenticate the user
LOG_ERROR	9007	Error: Unable to transfer data to ftp server: <IP Address>
LOG_ERROR	9009	Connection to <IP Address> failed, error code = <Error Code>
LOG_ERROR	9009	SSL Connection to <IP Address> failed
LOG_ERROR	9010	Out of memory for formatting logs
LOG_NOTICE	9013	Dropping logs, running low on memory
LOG_ERROR	9013	Error in hash generation or encryption
LOG_NOTICE	9014	Logging parameters are set for vip <IP Address>:<Port>
LOG_ERROR	9018	Unable to log the request since FTP server is slow or unreachable
LOG_ERROR	9018	Dropping logs since queue is full
LOG_ERROR	9019	Signature generation of logs failed
<b>Shared Symmetric Key (SSKEY)</b>		
LOG_WARN	41001	Encryption Key is going to expire within <Number> days", REMAINING_DAYS_FOR_EXPIRY( pSharedKey->keyExpiryTimeout,curTimeInSecs)
LOG_WARN	41002	Encryption Key has already expired
<b>BYPASS</b>		
LOG_ALERT	46001	Unit is switching to bypass mode
LOG_NOTICE	46002	State set to bypass: stopping heartbeat
LOG_NOTICE	46003	State set to normal: starting heartbeat
<b>Event Manager (EVM)</b>		
LOG_ERROR	11001	Event Manager startup failure: could not handle signals
LOG_ERROR	11007	EnableSyslogService: create socket failed
LOG_ERROR	11008	fopen <log_filename>: <error_description>
LOG_ERROR	11009	<log_filename> write failed <error_description>
<b>Heartbeat (HB)</b>		

LOG_ERROR	15001	Heartbeat events dropped, queue is full
LOG_ERROR	15002	Unable to bind to address
LOG_ERROR	15003	Error sending packet
LOG_ERROR	15003	Error receiving data From remote gateway
LOG_ERROR	15004	Attempting to reinitialize the Heartbeat Server before closing
LOG_ERROR	15004	Attempting to send data without Initialization
<b>Certificate (CERT)</b>		
LOG_NOTICE	17001	<ssl-function-name>: Trusted certificate expired: CN=<Common Name>, OU=<Org Name >
LOG_NOTICE	17001	<ssl-function-name>: Trusted certificate expired: O=<Org Name> L=<Location> S=<State> C=<City>
LOG_NOTICE	17500	Cert Initialization
<b>SSL and TLS (SSL)</b>		
LOG_NOTICE	16001	<ssl-function-name>: Base 0x<ssl-handle> - Access denied: received bad certificate signature
LOG_NOTICE	16001	<ssl-function-name>: Base 0x<ssl-handle> - Access denied: failed to verify certificate signature
LOG_NOTICE	16001	<ssl-function-name>: Base 0x<ssl-handle> - Access denied: certificate chain too long
LOG_NOTICE	16001	<ssl-function-name>: Base 0x<ssl-handle> - Access denied: failed to decode certificate
LOG_NOTICE	16001	<ssl-function-name>: Base 0x<ssl-handle> - Access denied: no certificate
LOG_NOTICE	16001	<ssl-function-name>: Base 0x<ssl-handle> - Access denied: failed to validate certificate chain
LOG_NOTICE	16001	<ssl-function-name>: Base 0x<ssl-handle> - Access denied: <Error Code>
	16002	SSL PMS Error
	16003	SSL DEC Error
LOG_NOTICE	16004	<ssl-function-name>: Base 0x<ssl-handle> - Sending alert: <Alert-desc> (<Alert Code>) from [<IP Address>:<Port>]
LOG_NOTICE	16005	<ssl-function-name>: Base 0x<ssl-handle> - Received alert: <Alert-desc> (<Alert Code>) from [<IP Address>:<Port>]
	16006	SSL FIN Error
	16010	SSL New Socket
	16011	SSL Delete Socket
LOG_NOTICE	16012	<ssl-function-name>: Base 0x<ssl-handle> - No RSA private key available
LOG_NOTICE	16012	<ssl-function-name>: Base 0x<ssl-handle> - Mismatched key size <Size> (expected <Size>)

LOG_NOTICE	16012	<ssl-function-name>: Base 0x<ssl-handle> - Failed to get authority private key
LOG_NOTICE	16012	<ssl-function-name>: Base 0x<ssl-handle> - Called on a client socket
LOG_NOTICE	16012	<ssl-function-name>: Base 0x<ssl-handle> - Called on a server
LOG_ERROR	16013	<ssl-function-name>: Out of memory
LOG_ERROR	16013	<ssl-function-name>: Base 0x<ssl-handle> - Out of memory
LOG_ERROR	16013	<ssl-function-name>: Socket 0x<sslsock-handle> - Out of memory
LOG_NOTICE	16014	<ssl-function-name>: Incorrect server name: length should be between 0 and < length >
	16015	SSL Message Error
LOG_ERROR	16016	<ssl-function-name>: Base 0x<ssl-handle> - Failed to schedule crypto command
	16017	SSL SEND Error
	16018	SSL RECV Error
LOG_NOTICE	16019	< ssl-function-name >: Cannot configure more than <Number> certificate policies
LOG_NOTICE	16020	<ssl-function-name>: Cannot configure more than <Number> trusted certificates per service
LOG_NOTICE	16021	<ssl-function-name>: No available SSL version for client socket
LOG_NOTICE	16023	<ssl-function-name>: Ephemeral Key changed
LOG_NOTICE	16024	<ssl-function-name>: Base 0x<ssl-handle> - No ephemeral key available
	16025	SSL Content Type Mismatch
	16026	SSL DN Constraint
	16027	SSL Certificate Decode Failure
	16028	SSL Certificate Unsupported
	16029	SSL Certificate Invalid Time
	16030	SSL Client Renegotiation
	16031	SSL Handshake Failure
	16040	SSL Session Timed Out
	16050	SSL General Notice
LOG_NOTICE	16500	SSL Initialization
<b>HTTP Proxy (HTTPSVC)</b>		
LOG_ERROR	00000	HttpRequestCtxDequeue Running out of contexts
LOG_ERROR	13100	HttpServerParseRequest: Parse failed; Malformed version <request-buffer>
LOG_ERROR	13100	HttpServerParseRequest: Parse failed; Unknown major number <request-buffer>

LOG_ERROR	13100	HttpServerParseRequest: Parse failed; Unknown minor number <request-buffer>
LOG_ERROR	13100	HttpServerParseRequest: Parse failed; Unknown method: <request-buffer>
LOG_ERROR	13100	HttpServerParseRequest: Parse failed; Malformed URL <request-buffer>
LOG_ERROR	13100	HttpServerParseRequest: Parse failed; Malformed line end <request-buffer>
LOG_ERROR	13101	HttpClientParseResponse: Parse failed; Malformed version <request-buffer>
LOG_ERROR	13101	HttpClientParseResponse: Parse failed; Unknown major number <request-buffer>
LOG_ERROR	13101	HttpClientParseResponse: Parse failed; Unknown minor number <request-buffer>
LOG_ERROR	13101	HttpClientParseResponse: Parse failed; Malformed status code <request-buffer>
LOG_ERROR	13101	HttpClientParseResponse: Parse failed; Header: <request-buffer>
LOG_ERROR	13101	HttpClientParseResponse: Parse failed; Malformed line end <request-buffer>
LOG_WARN	13103	OnHttpServerSockRecv: Session timed out from <Client IP:Port>
LOG_NOTICE	13200	Can not connect to server (< error-code >) for connection from: 0x< IP Address >
LOG_NOTICE	13200	SSL connection to server for connection from: 0x< IP Address > failed
LOG_NOTICE	13200	Error connecting to server (< error-code >) for connection from: 0x< IP Address >
LOG_NOTICE	13200	Error opening SSL connection to server for connection from: 0x< IP Address >
LOG_NOTICE	13200	SSL accept failed for connection from: 0x< IP Address >
LOG_NOTICE	13200	Error switching connection from: 0x< IP Address > to SSL
LOG_NOTICE	13200	Error accepting SSL connection from: 0x< IP Address >
<b>Web Authentication (WEBAUTH)</b>		
LOG_ERROR	18203	Unable to contact the authentication server, (RPC Queue full)
LOG_ERROR	18204	Remote procedure call to authentication server timed out
LOG_ERROR	18205	Login attempt failed for user <User ID>
LOG_ERROR	18206	Changing password failed for user <User ID>
LOG_NOTICE	18207	Added a realm:<Realm ID>
LOG_ERROR	18208	Unable to add realm:<Realm ID>
LOG_NOTICE	18209	Deleted a realm:<Realm ID>
LOG_ERROR	18215	Error received from webauthd , <Error String>

LOG_NOTICE	18216	Insert into ptrie - allocation failed (flags: 0x<internal-flags-value>, mem: <internal-mem-handle>) "Creating AuthzCache - inserting into ptrie failed(nodes: <internal-node-handle>, <internal-node-handle>
LOG_NOTICE	18217	Client attempted to Logout without login session cookie\n
LOG_WARN	18218	Invalid external policy store configured, realm name = <realm-name>
<b>Application Firewall (APS)</b>		
LOG_ERROR	19003	GetIpsUrlProfileLearningStats: error <Error_ID>
LOG_NOTICE	19031	XML Firewall error: <error-string> ( offset: <offset number>, code: <error code> )" ,pErr->desc,( int )pErr->offset, pErr->code
LOG_NOTICE	19031	XML Firewall error: Input validation
LOG_NOTICE	19031	XML Firewall error: Attack pattern
LOG_NOTICE	19031	XML Firewall error: Operation denied
LOG_NOTICE	19031	Received error from Web Services Firewall module: error desc (<Error Id>: <error message> )
LOG_ERROR	19032	Failed to allocate NCFORMINFO buffer
LOG_ERROR	19032	Unable to add session param to NCFORMINFO (no-name param)
LOG_ERROR	19032	Failed to allocate NCFORMINFO buffer(resp)
LOG_ERROR	19032	Unable to add session param to NCFORMINFO (multi-value)
LOG_ERROR	19032	Failed to allocate buffer for response URL rewrite
LOG_ERROR	19032	Failed to allocate buffer for form encryption
LOG_ERROR	19035	PfCSRFProtection: No CSRF token found
LOG_WARN	19500	Could not cloak match for <group name>. Value of Initial or Trailing Characters to Keep is too large
LOG_WARN	19500	POST request with both Content-Length and Transfer-Encoding headers [ url: <URL Malformed URL> ], dropped
LOG_WARN	19500	No intrusion information for intrusion ID
<b>Cookie Security (COOKIE)</b>		
LOG_ALERT	20003	Cookie expires: Client <IP Address>
LOG_ALERT	20004	Cookie auth failed: cookiename auth failed
LOG_ALERT	20005	Cookie Length Overflow: Client <IP Address>
LOG_ERROR	20006	Failed to allocate Shared Key context for cookie encryption
<b>CRL Daemon (CRL)</b>		
LOG_ERROR	40001	CRL File Download successfull
LOG_ERROR	40002	CRL File Download failed
<b>FTP Proxy (FTPSVC)</b>		
LOG_ERROR	21011	Error while transferring data
LOG_WARN	21014	<Internal Session ID> Invalid client ip-address (<IP Address>) specified with the port command, actual client ip-address is (<IP Address>)



LOG_WARN	21014	<Internal Session ID> Invalid port (<Port>) specified with the port command, port value must be greater than 1024
LOG_WARN	21014	<Internal Session ID> Invalid ip-addr (<IP Address>) used to connect to listening ftp data socket, expected from (<IP Address>)
LOG_ERROR	21022	Unable to allocate state control block for a session
LOG_ERROR	21022	Unable to allocate memory for ftp session
LOG_ERROR	21022	Out of memory
LOG_ERROR	21022	<Service IP Address:Port>:Unable to allocate memory for PORT cmd to FTP server
LOG_ERROR	21022	<Service IP Address:Port>:Unable to allocate memory for SSL verbs
LOG_ERROR	21023	Unable to get an active back-end server
LOG_ERROR	21024	Failed to create new socket
LOG_ERROR	21024	Failed to create SSL socket
LOG_ERROR	21024	Failed to create ssl client socket for data connection
LOG_ERROR	21025	Unable to bind a server for data connection
LOG_ERROR	21025	Unable to setup data connection
LOG_ERROR	21026	Failed to connect to FTP server
LOG_ERROR	21026	Unable to establish SSL control connection with the FTP server
LOG_ERROR	21026	Unable to connect to FTP server <Server IP Address>
LOG_ERROR	21027	Unable to accept SSL connection from FTP client
LOG_ERROR	21028	Failed to send response to the client
LOG_ERROR	21028	Failed to send control data to the server, because of small TCP windows
LOG_ERROR	21028	Failed to send data to the FTP client on the data connection
LOG_ERROR	21029	Failed to receive data from the FTP client on the data connection
LOG_ERROR	21029	Failed to receive data from FTP server on the data connection
LOG_ERROR	21030	Received bad response codes from the FTP server
<b>Compression (COMPRESS)</b>		
LOG_ERROR	24001	Compression request errored, <Error Code>, <Error String>
LOG_ERROR	24006	Failed to initialize compression, switching back to no-compression mode
<b>Web Translation (WATREWR)</b>		
LOG_ERROR	26051	Rewrite Module: URL rewrite by both Url-Translation and Request Rewrite
LOG_ERROR	26052	Rewrite Module: HTTP header rewrite by both URL-translation and Request Rewrite. Please go over your configuration to see if this can be avoided
<b>Network Socket (NET)</b>		
LOG_ERROR	3001	Failed to attach interface <Interface Name>

	3002	System Interface related
LOG_NOTICE	3003	<Interface Name>: promiscuous mode enabled
	3004 3005	System Interface related
LOG_ERROR	3011	rn_addmask: mask impossibly already in tree
LOG_ERROR	3011	Mask for route not entered
LOG_ERROR	3012	rn_delete <node-info>: Orphaned Mask <node-info> at <node-info>
LOG_ERROR	3013	rn_init: radix functions require max_keylen be set
	3014	System Route related
	3021-23	QOS related
	3031-48	NC Sockets related
<b>TCP (NETINET)</b>		
	4031 4032	INET IP related
LOG_ERROR	4033	Can't find virtual host for route, dst = <IP Address>
LOG_NOTICE	4034	ipflow to <IP Address> reached max refs
LOG_NOTICE	4034	Copyright (c) 2001, 2002 Barracuda Inc.
LOG_NOTICE	4034	Copyright (c) 1982, 1986, 1993 The Regents of the University of California
	4035 - 4046	INET IP related
	4051 - 4053	TCP connections related
LOG_ALERT	4054	Detected a SYN attack, using SYN cookies
	4055 - 4058	TCP connections related
	4071-86	Forwarding related
	4091-99	NATting related
	4001	ICMP Redirect
LOG_WARN	4011	arp request for <IP Address> failed with no memory
LOG_ERROR	4013	<Host IP Address> is using my IP address <IP Address>
LOG_ERROR	4014	Failed to find route for arp response to client <IP Address>
LOG_WARN	4015	arp: <MAC Address> attempts to modify permanent entry for <IP Address> on <Interface Name>
LOG_WARN	4016	arp_rtrequest: bad gateway value
LOG_ERROR	4017	arpresolve: can't allocate info for <IP Address>, rt=<route>
LOG_ERROR	4017	arp_rtrequest: malloc failed
	4111-16	UDP related
	4131-141	ICMP ERRORS related
LOG_ERROR	45006	Socket between stm wrapper and Configuration agent failed...Cannot execute <command> command

<b>Symmetric Encryp. Decryp. (CRYPTO)</b>		
LOG_DEBUG	5004	Decrypt Failed
<b>Process Monitor (PROCMON)</b>		
LOG_WARN	44001	STM crash detected current state is: <STM State> state <Number> crashes in last <Time in Seconds>
LOG_NOTICE	44001	Checking if configuration needs to be synchronized with peer system
LOG_NOTICE	44001	Notifying peer system to check if configuration needs to be synchronized
LOG_WARN	44002	Total retries: <Number> waiting for <Time in seconds> before next restart
LOG_WARN	44003	Too many <Number> tries to restart unstable STM, switching to Failed state
LOG_WARN	44004	Too many STM crashes switching to Unstable state, will attempt restart in <Time in seconds>
LOG_NOTICE	44005	Attempting to restart STM and Eventmgr
LOG_NOTICE	44006	Attempting to recreate the log DB
LOG_ERROR	44007	Error : <Error code> encountered with stm start
LOG_ERROR	44008	STM restart failed: switching to Failed state
LOG_ERROR	44009	STM restart failed: switching to Failed state
LOG_NOTICE	44010	STM restart succeeded: current state: Stable
LOG_WARN	44011	shmget failed
LOG_WARN	44012	number of stm worker threads is <Number of STM Threads>"
LOG_WARN	44013	shmread error <Failure Error>
LOG_WARN	44014	STM worker thread <Number> seems to be hung. Event count <Number>
LOG_WARN	44015	STM seems to be hung. Killing STM
LOG_NOTICE	44016	STM alive: switching from <STM State> to stable state
LOG_WARN	44017	<Process Name> state is <Process State>
LOG_ERROR	44018	bypass_hbeat.pl is dead restarting gpio and bypass_hbeat
LOG_ERROR	44019	clamd is dead, restarting <Process Name>
LOG_ERROR	44019	snmpd is dead, restarting <Process Name>
LOG_ERROR	44020	profile agent is dead, restarting <Process Name>
LOG_ERROR	44021	collectd is dead, restarting <Process Name>
LOG_ERROR	44022	namemon is dead, restarting namemon
LOG_ERROR	44023	config agent is dead, restarting config_agent and stm
LOG_CRIT	44024	System highest temp has reached
LOG_CRIT	44025	System is getting real hot
LOG_CRIT	44026	System highest temp has reached

LOG_CRIT	44027	System is getting real hot
LOG_ALERT	44028	One of the CPU fans is dead
LOG_ALERT	44029	One of the System fans is dead
LOG_ALERT	44030	One of the System fans is dead
LOG_ALERT	44031	Firmware storage exceeds 85%
LOG_ALERT	44032	Mail storage exceeds 85%
LOG_ALERT	44033	One of the RAID arrays is degrading.
LOG_NOTICE	44034	<Interface Name>: link seems down
LOG_ALERT	44035	<Interface Name>: link is down
LOG_ALERT	44036	<Interface Name>: link is up
LOG_NOTICE	44001	Checking if configuration needs to be synchronized with peer system
LOG_NOTICE	44001	Notifying peer system to check if configuration needs to be synchronized
LOG_ERROR	44039	heartbeat.pl is dead <Number>, restarting
LOG_ERROR	44040	heartbeat.pl is in state D for <Number> tick(s). Ignoring the state
LOG_ERROR	44041	cluster_manager is dead <Number>, restarting
LOG_ERROR	44042	cluster_manager is in state D for <Number> tick(s). Ignoring the state
LOG_ERROR	44042	Restarting spinal cord process since there may be an issue in connecting to Control Center
LOG_ERROR	44043	Restarting ssh
LOG_NOTICE	44043	Restarting syslog-ng process as it was down
LOG_NOTICE	44001	Checking if configuration needs to be synchronized with peer system
LOG_ERROR	44044	Configuration dispatcher is dead <Number>, restarting
LOG_ERROR	44045	Configuration dispatcher is in state D for <Number> tick(s). Ignoring the state
LOG_ALERT	44046	STM seems to be running high on Memory. Please contact to Barracuda Networks Support Center for analysis
LOG_ALERT	44047	Memory Usage exceeds 70%
LOG_NOTICE	44048	Monitoring links: <Link Name>
LOG_NOTICE	44049	Started monitoring
LOG_ALERT	44050	Log storage exceeds 85%
LOG_ALERT	44051	High CPU Usage
LOG_EMERG	44850	VNET_CONFIG' @message if \$syslog ne 0;
LOG_NOTICE	44201	Mode change: Hard bypass = <Hard Bypass Enabled> Bypass on Failure = <Soft Bypass Enabled>
LOG_NOTICE	44202	Mode set to bypass Hard bypass = <Hard Bypass Enabled> Bypass on Failure = <Soft Bypass Enabled>

LOG_NOTICE	44203	Changing Heartbeat bit state from <Old Hearbeat bit state> to <New Hearbeat bit state>
LOG_NOTICE	44204	Mode set to never bypass
LOG_ALERT	44301	Harddisk Failure
LOG_ERROR	44701	Could not open pdf '<report>' because: \$!\n
LOG_ERROR	44702	Could not open html '<report>' because: \$!\n
LOG_ERROR	44703	Report not sent to <email address>
<b>CLUSTER MANAGER (CLRMGR)</b>		
LOG_NOTICE	43001	We are not yet in cluster mode. Could not calculate destination IP and destination Identity. Exiting
LOG_NOTICE	43001	Invalid Role : <PRIMARY/BACKUP:self_role> specified in cluster.conf. Could not determine self role. Exiting
LOG_ERROR	43001	Cluster.conf file is not existing...Exiting
LOG_ALERT	43001	Peer device \$g_peer_ip is UP
LOG_ALERT	43002	Peer device \$g_peer_ip is UP
LOG_ALERT	43003	Peer device \$g_peer_ip DOWN
LOG_NOTICE	43010	Self assume received for <operational_mode> mode
<b>Monitor Check (CHECK_MON_LINK)</b>		
LOG_ERROR	48302	Couldn't connect to NTP server: <Server Name/IP Address>
<b>Barracuda Updates (UPDATE)</b>		
LOG_ALERT	52001	Energize update subscription is about to expire in <Number> days
LOG_ALERT	52002	New attack definition version <Number> is available
LOG_ALERT	52003	New firmware update is available Current Version = <current_version> Beta Version = <beta_version>
LOG_ALERT	52004	New firmware update is available Current Version = <current_version> New Version = <new_version>
LOG_ALERT	52005	Attackdef downloaded and applied on the appliance
LOG_ALERT	52006	Attackdef downloaded and applied on the appliance
LOG_ALERT	52007	New Virus definition update available.Current Version = <current_version>. New Version = <new_version>
LOG_ALERT	52010	New Firmware update available.Current Version = <current_version>. New Version = <new_version>
LOG_ALERT	52011	New Attack definition update available.Current Version = <current_version>. New Version = <new_version>
LOG_ALERT	52012	New Virus definition update available.Current Version = <current_version>. New Version = <new_version>.
<b>BYPASS</b>		
LOG_ALERT	44221	Unit is switching to bypass mode

LOG_NOTICE	44222	State set to bypass: stopping heartbeat
LOG_NOTICE	44223	State set to normal: starting heartbeat
LOG_NOTICE	44201	Mode change: Hard bypass = <Hard Bypass Enabled> Bypass on Failure = <Soft Bypass Enabled>
LOG_NOTICE	44202	Mode set to bypass Hard bypass = <Hard Bypass Enabled> Bypass on Failure = <Soft Bypass Enabled>
LOG_NOTICE	44203	Changing Heartbeat bit state from <Old Hearbeat Version> to <New Hearbeat Version>
LOG_NOTICE	44204	Mode set to never bypass
<b>STM_WRAPPER</b>		
LOG_WARN	45001	Cannot execute <Command Name> Command. Exiting.
LOG_WARN	45002	Configuration agent is not running. Cannot monitor <Command Name> command
LOG_WARN	45003	command<Command Name> execution status = <Status>
LOG_WARN	45004	Configuration agent crashed. Failed to execute <Command Name> command
LOG_WARN	45005	Configuration agent is not running....Cannot execute <Command Name> command
LOG_WARN	45006	Socket between stm wrapper and Configuration agent failed...Cannot execute <Command Name> command
LOG_ERROR	45007	Failed to initialize STM
LOG_NOTICE	45008	Successfully initialized STM
LOG_NOTICE	45008	Creating db snapshot after initwac
LOG_NOTICE	45009	Successfully stopped STM
LOG_NOTICE	45010	<Failure Reason>
LOG_INFO	45011	Procmon rollback :Loading at <Date> from DB snapshotlast successful digest
LOG_NOTICE	45012	Rollback finished: success
LOG_ERROR	45013	Rollback failed : Failed to restart STM
LOG_NOTICE	45014	<Failure Reason>
LOG_WARN	45016	Configuration size is <Current Config Size> Bytes which exceeds the <Max Config Size> Bytes safe limit. Please check your configuration.
LOG_WARN	45018	System in failed state: attempting recovery for config
LOG_ERROR	45019	STM startup failed. Retrying with blank config
LOG_ERROR	45020	STM startup failed even with blank config. Exiting
LOG_NOTICE	45022	Committing UI configuration
LOG_NOTICE	45024	Killing STM for dumping core
<b>PROCESS SCHEDULE</b>		

LOG_WARN	49001	Scheduled Backup failed : System has locked key configuration
<b>Stateful Failover (SFO)</b>		
LOG_NOTICE	25050	Opening System State Transfer listening socket
LOG_NOTICE	25050	Closing System State Transfer listening socket
LOG_NOTICE	25050	Accepted System State Transfer connection sock
LOG_NOTICE	25100	Unrecognised state pkt
LOG_NOTICE	25100	Calling update system state function of module
LOG_NOTICE	25100	Ignoring System State Transfer packet for unknown module
LOG_NOTICE	25150	Opening Request State Transfer listening socket
LOG_NOTICE	25150	Listening for Request State Transfer connections on socket
LOG_NOTICE	25150	Request State Transfer listening socket
<b>Admin Management</b>		
LOG_ALERT	51001	<user_role> User has logged in
LOG_ALERT	51015	Unable to reach Barracuda update server. Please check your network connectivity
LOG_ALERT	51002	LOG Database is corrupted. Please contact Barracuda Support
LOG_ALERT	51002	Summary Log Database is corrupt. Initializing DB recovery
LOG_ALERT	51005	Backup failure notification
LOG_ALERT	51004	FTP of access logs Failed. Reason:<message>
LOG_ALERT	51006	Performance numbers for this unit is not available <box_model>
LOG_ALERT	51009	Backup was successfully restored
LOG_WARN	51012	Disabling reporting as we are connected to BRS
LOG_WARN	51012	Enabling reporting as we are disconnected from BRS
LOG_WARN	51014	Unable to reach Barracuda update server in last <time_frame> minutes
LOG_NOTICE	51003	Error in logging to LOG Database.Please contact Barracuda Support
LOG_NOTICE	51013	Connectivity to Barracuda update server restored
<b>Configuration Synchronization</b>		
LOG_NOTICE	53003	This configuration change was successfully committed on the peer system
LOG_ERROR	53004	Failed sync configuration from namemon master node with serial : <namemon_master_node>
LOG_NOTICE	53005	Starting sync configuration from namemon master node with serial : <namemon_master_node>
LOG_NOTICE	53006	Completed sync configuration from namemon master node with serial : <namemon_master_node>
LOG_NOTICE	53007	Not notifying peer devices since bootstrapping is not done yet.
LOG_NOTICE	53008	Not syncing from best remote node:\$best_remote_node since bootstrapping is not done yet

© Barracuda Networks Inc., 2024 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.