

Barracuda Message Archiver Hardware Specifications

<https://campus.barracuda.com/doc/41098568/>

Barracuda Message Archiver Form Factor

| Model | Form Factor (Prior to November 2014) | Form Factor (November 2014 and Later) |
|--------------|---|--|
| 150 | Rack mountable - 1U | Rack mountable - 1U |
| 350 | Rack mountable - 1U | Rack mountable - 1U |
| 450 | Rack mountable - 1U | Rack mountable - 1U |
| 650 | Rack mountable - 1U | Rack mountable - 1U |
| 850 | Rack mountable - 2U | Rack mountable - 2U |
| 950 | Rack mountable - 2U | Rack mountable - 3U |
| 1050 | Rack mountable - 3U | Rack mountable - 4U |

Barracuda Message Archiver Weight and Dimensions

| Model | Weight in Pounds | Dimensions in Inches (D x W x H) |
|--------------|-------------------------|---|
| 150 | 11 | 10.5 x 17.2 x 1.75 |
| 350 | 33 | 20 x 17.2 x 1.75 |
| 450 | 33 | 20 x 17.2 x 1.75 |
| 650 | 33 | 20 x 17.2 x 1.75 |
| 850 | 75 | 25.5 x 17.2 x 3.5 |
| 950 | 66 | 25.5 x 17.2 x 5.25 |
| 1050 | 108 | 27.5 x 17.2 x 7 |

Barracuda Message Archiver Network Interface Card

The Barracuda Message Archiver model 650 and higher contains two network interface cards (NICs) that you can place on separate networks to increase bandwidth. Note that you cannot team, that is, add, the NICs together .

| Model | Number of Interfaces |
|--------------|-----------------------------|
|--------------|-----------------------------|

| | |
|------|---|
| 150 | 1 |
| 350 | 1 |
| 450 | 1 |
| 650 | 2 |
| 850 | 2 |
| 950 | 2 |
| 1050 | 2 |

10 Gigabit Ethernet Card Standard

Models 650/850/950/1050 include a 10 Gigabit Ethernet card. If your organization's environment does not support 10 Gigabit throughput, the card reduces its speed to 1 Gigabit:

- **1 Gigabit Connection** - Plug in a CAT5e cable for 1 Gigabit throughput.
- **10 Gigabit Connection** - Plug in a CAT6e cable and a 10 Gigabit switch for 10 Gigabit throughput.

Barracuda Message Archiver 950 and 1050 Drive Layout

Model 950 (3U) and 1050 (3U) Drive Layout

| | | | |
|-------|-------|--------------|--------------|
| Drive | Drive | <i>empty</i> | <i>empty</i> |
| Drive | Drive | <i>empty</i> | <i>empty</i> |
| Drive | Drive | <i>empty</i> | <i>empty</i> |
| Drive | Drive | Drive | <i>empty</i> |

Model 1050 (4U) Drive Layout

Device Front

| | | | |
|-------|-------|-------|-------|
| Drive | Drive | empty | empty |
| Drive | Drive | empty | empty |
| Drive | Drive | empty | empty |
| Drive | Drive | empty | empty |
| Drive | Drive | Drive | empty |
| Drive | Drive | Drive | empty |

Device Back

| | | | |
|-------|-------|-------|-------|
| Drive | Drive | Drive | Drive |
| Drive | Drive | Drive | Drive |
| Drive | Drive | Drive | Drive |

Barracuda Message Archiver AC Input Voltage Range

| Model | AC Input Range | BTU/hr |
|-------|----------------|-------------|
| 150 | 120-230V | 737 BTU/hr |
| 350 | 120-230V | 983 BTU/hr |
| 450 | 120-230V | 983 BTU/hr |
| 650 | 120-230V | 1679 BTU/hr |
| 850 | 120-230V | 1679 BTU/hr |
| 950 | 120-230V | 2661 BTU/hr |
| 1050 | 120-230V | 3562 BTU/hr |

Barracuda Message Archiver Appliance Wattage/Thermal Output

| Model | Input Current (Amps AC) | Watts | BTU/hr |
|-------|-------------------------|-------|-------------|
| 150 | 1.8 | 216 | 737 BTU/hr |
| 350 | 2.4 | 288 | 983 BTU/hr |
| 450 | 2.4 | 288 | 983 BTU/hr |
| 650 | 4.1 | 492 | 1679 BTU/hr |
| 850 | 5.1 | 612 | 1679 BTU/hr |
| 950 | 6.5 | 780 | 2661 BTU/hr |

| | | | |
|------|-----|------|-------------|
| 1050 | 8.7 | 1040 | 3562 BTU/hr |
|------|-----|------|-------------|

For more information on calculating the power consumption in watts, see [Barracuda Product Power Consumption in Watts](#).

Figures

1. 950_3U_drive_layout.png
2. 1050_4U_drive_layout.png

© Barracuda Networks Inc., 2020 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.