

Getting Started - Control Center

<https://campus.barracuda.com/doc/73719450/>

For Firewall Control Centers installed via Barracuda F-Series Install, do not use the CC Wizard. For more information, see [Getting Started - Control Center without CC Setup Wizard](#).

Complete the CC Wizard to configure all necessary box layer and Control Center settings. The CC Wizard can be launched from the **OPTIONS** menu or automatically starts when logging into a new Control Center on box layer.

Before You Begin

- The CC Wizard can be used only on new or freshly installed Control Centers.
- Virtual Control Centers require a license token for activation. The license token is included in the email received from Barracuda Customer Support after purchasing the Control Center license.

Step 1. Start the CC Wizard

The CC Wizard will launch automatically when logging in to a new Control Center or can be launched from the **OPTIONS** menu in Barracuda Firewall Admin:

Wizard Starts Automatically on First Login

Log into the Box Layer of a new Control Center to use the CC Setup Wizard.

1. Launch Barracuda Firewall Admin.
2. Select **Firewall** to log into the Control Center box layer:
 - **IP Address / Name** – If you are using a hardware Control Center appliance, enter 192.168.200.200. For virtual Control Centers, enter the IP address you set during deployment.
 - **Password** – Enter the default password: ngf1r3wall.



Firewall Control Center SSH

IP Address / Name

Username

Password


Add to Favorites

3. Click **Sign In**. The **CC Setup Wizard** window opens.


Launch the CC Wizard Manually

The CC Setup Wizard can also be accessed by the **OPTIONS** menu in Barracuda Firewall Admin.

1. Launch Barracuda Firewall Admin.
2. Click the **OPTIONS** menu in the upper left-hand corner and click **CC Wizard**. The **CC Setup Wizard** window opens.



3. Log in to the Control Center:
 - **Management IP** – If you are using a hardware Control Center appliance, enter 192.168.200.200. For virtual Control Centers, enter the IP address you set during deployment.
 - **Password** – Enter the default password: ngf1r3wall.



4. Click **Next**.


Step 2. Enter your Company Data

You must enter your company data to supply the information needed for:

- Control Center license activation
- Box level certificates
- CC certificates
- Activation template used on the Control Center to activate managed CloudGen Firewalls.
- System email address.

1. Enter the following information:

- **Company Name**
- **Department**
- **First Name**
- **Last Name**
- **Certificate Common Name**
- **Email** - After successful activation, a confirmation email is sent to this email address.
- **Country**
- **State**
- **City**
- **Street**
- **ZIP/Postal Code**
- **Phone**



Barracuda Firewall Control Center Wizard

Company Data

Activation

Administrative Settings

Network Configuration

Create Administrators

Summary

Submit

Barracuda | Firewall Control Center

Company Information

The data provided here will be used for activation and for the certificates identifying this Barracuda Firewall Control Center

Company Name (Organization)

Department (Organizational Unit)

First Name

Last Name

Certificate Common Name

Email

Country

State

City

Street

Zip/Postal Code


Phone

2. Click **Next**.


Step 3. Activate the Control Center

Accept the **Terms of Use** to download, install, and activate the licenses. If you are using a virtual Control Center, you are prompted to enter the license token you received from Barracuda Customer Support after purchasing the license. Customer data entered in Step 1 is used to complete the contact information in the activation form.


1. Click **Accept and Activate**.



2. If you are using a virtual Firewall Control Center, enter the **License Token**: E.g., XXXXX-XXXXX-XXXXX




3. Click **Next**.



Step 4. Administrative Settings

Enter administrative settings for your Control Center. Enabling the Revision Control System (RCS) is strongly recommended.

1. **Change the root user password.** Depending on the password strength, the background of the **New password** textbox is green (strong), yellow (medium), or red (weak).
2. Enter the **DNS Settings**:
 - **DNS Server** – Enter the IP address for the primary DNS server on your network.
 - **Default Domain** – Enter the default domain.
3. Enter the **NTP Settings**:
 - **NTP Server** – Enter an IP address or hostname for your preferred NTP server.
 - **Timezone** – Select the time zone from the dropdown.
4. Enable **Revision Control System (RCS)**:
 - **Enable RCS (recommended)** – Enable to allow the administrator to view and, if necessary, revert configuration changes made on the Control Center.
 - **Require RCS Change Messages** – Enable this option to force the admin to enter a description for every configuration change.



The screenshot shows the 'Barracuda Firewall Control Center Wizard' window. On the left, a vertical progress bar indicates the current step is 'Administrative Settings', with other steps like 'Company Data', 'Activation', 'Network Configuration', 'Create Administrators', 'Summary', and 'Submit' shown as completed or pending. The main content area is titled 'Administrative Settings' and contains the following sections:

- Change the root user password**: Includes a 'New password' field with a green background, a 'Confirm new password' field, and a 'Back' button.
- DNS Settings**: Includes a 'DNS Server' text box with '10.0.10.100' and a 'Default Domain' text box with 'doc.org'.
- Time Settings**: Includes an 'NTP Server' text box with 'poolntp.org' and a 'Timezone' dropdown menu set to 'Europe/Berlin'.
- Revision Control System (RCS)**: Includes a checkbox for 'Enable RCS (recommended)' which is checked, and a checkbox for 'Require RCS Change Messages' which is unchecked.

At the bottom of the wizard, there are 'Cancel', 'Back', and 'Next' buttons. The 'Next' button is highlighted with an orange border.


5. Click **Next**.

Step 5. Network Configuration

Configure basic network settings, such as management and Control Center IP address, gateway

routes, and trusted networks (management ACLs).

1. Enter a **Hostname** for your CC.
2. (optional) Change the **Management IP**.
3. Select the **Netmask** from the dropdown.
4. Enter the **Control Center IP**. This IP address must be different from the management IP address.
5. Enter the **Default Gateway**.
6. (optional) Enter all **Trusted Networks** that are allowed to access the Control Center.
Incorrect trusted networks (management ACLs) prevent you from connecting to your Control Center. For more information, see [How to Change the Root Password and Management ACL](#).
7. For each **Additional Gateway Route**:
 1. Enter the destination **Network** and **Gateway**.
 2. Click **Add**.



The screenshot shows the 'Barracuda Firewall Control Center Wizard' window. The 'Network Configuration' step is active, indicated by a blue dot on the left sidebar. The main content area is titled 'Barracuda | Firewall Control Center' and contains the following fields:

- Network Configuration:**
 - Hostname: DOC-CC2
 - Management IP: 10.0.10.37
 - Netmask: 25-Bit / 255.255.255.128
 - Control Center IP: 10.0.10.38
 - Default Gateway: 10.0.10.1
- Trusted Networks - Access Control List:**
 - Trusted Networks: (empty text box)
- Additional Gateway Routes:**
 - Network: (empty text box) Gateway: (empty text box) [Add]
 - Network: 10.17.0.0/16 Gateway: 10.0.10.1 [Delete]

At the bottom, there are 'Cancel', 'Back', and 'Next' buttons. The 'Next' button is highlighted with a red box.


8. Click **Next**.

Step 6. (optional) Create Administrators

You can create additional administrators. All administrators created have full read/write permissions on the Control Center and also full access to the box layer. If you want to use an external authentication server, create the CC admins after completing the CC Wizard. For more information, see [Control Center Admins](#).

1. For each additional administrator, enter the following settings and click **Add**.

- **Username** – Enter a username.
- **Full Name** – Enter the full name of the user.
- **Password / Confirm Password** – Enter a password. Depending on the password strength, the background of the **Password** textbox is green (strong), yellow (medium), or red (weak).



The screenshot shows the 'Create Administrators' step of the Barracuda Firewall Control Center Wizard. On the left is a vertical progress bar with steps: Company Data, Activation, Administrative Settings, Network Configuration, Create Administrators (highlighted), Summary, and Submit. The main content area has a blue header with the Barracuda logo and 'Firewall Control Center'. Below the header, the text reads: 'Create Administrators. In addition to the root user, you can create further administrators. Additional administrators have full read/write permission on the NextGen Control Center.' There are four input fields: 'Username' (containing 'jond'), 'Full Name' (containing 'Jon Doe'), 'Password' (containing '*****'), and 'Confirm Password'. There are 'Add' and 'Delete' buttons next to the fields. At the bottom are 'Cancel', 'Back', and 'Next' buttons.

2. Click **Next**.

Step 7. Review Configuration Summary

1. (optional) Click **Print Summary** to print the configuration settings on the systems default printer.
2. (recommended) Click **Save Summary** to save a text file containing the configuration parameters collected by the CC Setup wizard.
3. Click **Next**.

Step 8. Submit the Configuration

The CC Wizard now sends and activates all configuration settings collected in steps 1 to 7. If one configuration step fails, use the **Back** button to go back and change the configuration. You can then resubmit the settings to finish the configuration of the Control Center. When the configuration changes are complete, click **Finish**. The CC Setup Wizard is automatically disabled for this Control Center.

Next Steps

Use the CC IP Address to connect to the Control Center.



Firewall
 Control Center
 SSH

IP Address / Name

Username

Password

Add to Favorites

	Link
Create Admins	Control Center Admins
Configure Central Management	<ul style="list-style-type: none"> • Central Management • How to Manage Ranges and Clusters
Add a CloudGen Firewall to the Control Center	<ul style="list-style-type: none"> • How to Add a new F-Series Firewall to the Control Center • How to Configure a Remote Management Tunnel for an F-Series Firewall
Licensing for managed CloudGen Firewalls	<ul style="list-style-type: none"> • How to Assign and Activate Single Licenses on a Control Center • How to Install and Assign Pool Licenses on a Control Center
Revision Control System (RCS)	Revision Control System (RCS)

Figures

1. getting_started_01.png
2. cc_wizard_02.png
3. cc_wizard_03.png
4. cc_wizard_04.png
5. cc_wizard_05.png
6. cc_wizard_06.png
7. cc_wizard_07.png
8. cc_wizard_08.png
9. cc_wizard_12.png
10. cc_wizard_13.png
11. cc_wizard_15.png

© Barracuda Networks Inc., 2019 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.