

## Setting the Objects a User Account Can Access

<https://campus.barracuda.com/doc/90440864/>

You can give access to different objects to set security controls for each user. You can set which sites, groups, devices and websites a user can access.

**Sites** When a user is allowed access to a site, that user can access all devices and websites that belong to the site, even in service groups that are not site-specific.

**Service Groups** When a user is allowed access to a service group, that user can access all devices from all sites that belong to the service group.

**Site Groups** When a user is allowed access to a site group, that user can access all devices that belong to the site group.

**Devices** When a user is allowed access to a device, that user can access all controls for the device. If a user is not allowed access to a group that contains the device, the user is able to access the group but only sees devices to which access has been granted.

**Cloud Services** When a user is allowed access to a cloud service, that user can access all controls for the website.

If the user has the role of **Administrator**, the user automatically has access to all objects. To customize object access, the user must be part of a role other than **Administrator**. See [Adding a Role to a User Account](#).

1. In Service Center, click **Configuration > User Management**.
2. Click the user for which you want to set object access.
3. Click the **Object Access** tab.
4. Click **Add**.
5. From the **Select the Type of Object to Add** list, select the object type (**Device, Group, Site** or **Website**).
6. Click **OK**.  
A listing for the selected object types appears.
7. Select all the required items from the list.
8. Click **Add**.
9. Click **Save**.

### See Also

[Denied Users](#)

[Removing the Objects a User Account Can Access](#)

© Barracuda Networks Inc., 2021 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.