

How to Back Up and Restore Secure Connector, Secure Access Controller, and Control Center Configurations

<https://campus.barracuda.com/doc/90445106/>

The configuration of the Secure Connector and the Secure Access Controller is stored in the archive.par of the Control Center, whereas the box layer configuration of the Control Center itself is stored in the box.par of the Control Center. The back up and restore process of a Secure Access Controller works in the same way as on the CloudGen Firewall.

Contact Barracuda Support to migrate beyond a back up or restoration.

To back up the configuration of your infrastructure:

1. Create a box.par file on the Control Center to save the box layer configuration of the Control Center.
2. Create an archive.par file to save the configuration of all managed firewalls, the Secure Controller, and the Secure Connector.

To restore the configuration of your infrastructure:

1. Import the box layer configuration of your Control Center from the box.par.
2. Import the Control Center configuration of all your devices in the Control Center with the archive.par.
3. In the restored Control Center, export the configuration of your Secure Access Controller in a box.par file.
4. On the Secure Access Controller, import the configuration from the created PAR file.

Back Up Your Infrastructure

Step 1. Back Up Your Control Center Box Layer

1. Log into the box layer of the Control Center.
2. Go to **CONFIGURATION > Configuration Tree**.
3. Right-click **Box** and select **Create PAR file**. The **Save As** window opens.
4. Select the archive type:
 - o **PAR File (*.par)** (default)
 - o **Compressed PAR File (*.pgz)**
 - o **Encrypted PAR File (*.pca)**
5. If you selected **Encrypted PAR file**, the **Password** window opens.
6. Click **Use Serial Number** or enter the **Password** manually.

The **box.par** file is saved to your local hard drive.

Step 2. Back Up Your Control Center Configuration

1. Log into the Control Center.
2. Go to **CONFIGURATION > Configuration Tree**.
3. Right-click the **Multi-Range** and select **Create PAR file**.
4. The **Save As** window opens.
5. Select the archive type:
 - **PAR File (*.par)** (default)
 - **Compressed PAR File (*.pgz)**
 - **Encrypted PAR File (*.pca)**
6. If you selected **Encrypted PAR file**, the **Password** window opens.
7. Click **Use Serial Number** or enter the **Password** manually.

The **archive.par** file is saved to your local hard drive.

Restore Your Infrastructure

Step 1. On Your Control Center, Import the Box Layer of Your Control Center

1. Log into the box layer of the Control Center.
2. Go to **CONFIGURATION > Configuration Tree**.
3. Right-click **Box** and select **Restore from PAR file**. Select the required PAR / PGZ / PCA file.
4. If you are using a PCA file encrypted with a manual password, enter the **Password** and click **OK**.
5. Click **Activate**.
6. Go to **CONTROL > Box**
7. In the left navigation menu, expand **Operating System** and click **Firmware Restart**. Click **Yes** to confirm that you want to restart the subsystem.
8. Expand **Network** and click **Activate new network configuration**.
9. Select one of the following network configuration activation modes:
 - If you are continuing to use the same management IP address and management port, click **Failsafe**.
 - If the new management IP address and management port are different from the ones currently configured on the appliance, click **Activate now**.
For information, see [How to Activate Network Changes](#).

Step 2. On Your Control Center, Import the Configuration

1. Log into the Control Center.
2. Go to the **CONFIGURATION > Configuration Tree** page. If you are prompted with warning messages, click **no**.
3. Right-click **Multi-Range** and select **Restore from PAR file**.

4. Select the required **archive.par** file.
5. (Optional) If the license has changed, you must also import the base license of the box layer on the Control Center. For more information, see [How to Manually Install the Licenses for the Control Center](#).

If you are restoring the configuration of a Control Center that has been reinstalled after a system crash, you must also restore the configurations of the appliances that it manages.

Step 3. On Your Control Center, Export the Configuration of Your Secure Access Controller

1. Log into the Control Center.
2. Click the **CONFIGURATION** tab.
3. In the **Configuration Tree**, navigate to the range and cluster for the Secure Access Controller.
4. Expand **Boxes**, right-click the Secure Access Controller, and select **Create PAR file for box**.
5. Select the archive type:
 - **PAR File (*.par)** (default)
 - **Compressed PAR File (*.pgz)**
 - **Encrypted PAR File (*.pca)**
6. If you selected **Encrypted PAR file**, the **Password** window opens.
7. If you selected **Encrypted PAR file**, click **Use Serial Number** or enter the **Password** manually.
8. Save the PAR file to your local hard drive.

Step 4. On Your Secure Access Controller, Import the Configuration of Your Secure Access Controller

1. Log into the Secure Access Controller.
2. Go to the **CONFIGURATION > Configuration Tree** page.
3. Right-click **Box** and select **Restore from PAR file**. Select the PAR or PCA file you previously created for this Secure Access Controller in the Control Center.
4. If you are using a PCA file encrypted with a manual password, enter the **Password** and click **OK**.
5. (Optional) Click **OK** to confirm the Emergency Override warning message.
6. Click **Activate**.
7. Go to the **CONTROL > Box page**.
8. In the left navigation pane, expand **Operating System** and click **Firmware Restart**. Click **Yes** to confirm that you want to restart the subsystem.
9. Expand **Network** and click **Activate new network configuration**.
10. Select one of the following network configuration activation modes:
 - If you are continuing to use the same management IP address and management port, click **Failsafe**.
 - If the new management IP address and management port are different from the ones currently configured on the appliance, click **Activate now**. For information, see [How to Activate Network Changes](#).

Further Information

- [How to Back Up and Restore Firewall, Secure Access Controller and Control Center Configurations](#)
- [How to Backup and Restore CC Archive Par Files on the Command Line](#)

© Barracuda Networks Inc., 2020 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.