
How to Create an Application Resource

<https://campus.barracuda.com/doc/39813726/>

Application resources are shortcuts to predefined application definitions and the necessary complementary configuration settings. When the user clicks the application resource the application is started with the settings provided by the administrator. Follow these steps to create an application resource.

Step 1. Create an application resource

1. Log in to the SSL VPN Web interface.
2. Go to the **RESOURCES > Applications** page.
3. Verify that you have selected the correct user database on the top right of the page.
4. In the **Create Application** section, enter a **Name**. E.g., OfficeCitrix
5. Select the application definition from the **Application** list. You may need to click the application category to see the entry in the list. E.g., Citrix Published Applications
6. Enter the required configuration settings. E.g., **hostname** for the Citrix server
7. In the **Available Policies** section, select the policies that you want to apply to the application and click **Add**.
8. Click **Add** to create the application.

The new application resource is created and displayed in the **Applications** section.

Step 2. (optional) Edit advanced settings for the application resource

In the **Applications** section click the **Edit** link next to the application to configure additional options.

Step 3. Launch the application

1. In the **Applications** section, click the **Launch** next to the application to test it.
2. When you are ready to make the application available to your users, click the **Edit** link associated with the resource in the **Applications** section.
3. Select the resource categories that you want to apply to the application in the **Resource Categories** section, and then click **Add**.
4. Click **Save**.

© Barracuda Networks Inc., 2020 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.