

How to Configure Administrative Roles

<https://campus.barracuda.com/doc/43847284/>

As part of an administrative profile, administrative roles define the operative permissions and restrictions of an administrative user to the different services of the Barracuda NG Control Center and the managed Barracuda NG Firewalls units. When configuring administrative roles, you can define which services the administrative user is allowed to access and which operations they are allowed or denied to perform on the services. You can then assign the role to an administrative profile (see [How to Configure Administrative Profiles](#)).

In this article:

Roles Permissions and Restrictions

Administrative roles permissions and restrictions are defined as follows:

Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
-----------------	----------------------	----------------	-----------------	-----------------	---------------	-----------------------

CC Configuration	Access to CC Config	Yes	Yes	Yes	Yes	Yes
	Kill Sessions	Yes	Yes	No	Yes	No
	Change Permissions	Yes	No	No	Yes	No
	Change Events	Yes	No	No	Yes	No
	Show Admins	Yes	No	Yes	Yes	No
	Manage Admins	Yes	No	No	Yes	Yes
	Create/Remove Range	Yes	No	No	Yes	No
	Create/Remove Cluster	Yes	No	No	Yes	No
	Use RCS	Yes	No	Yes	Yes	No
	Create/Remove Boxes	Yes	No	No	Yes	No
	Create/Remove Servers	Yes	No	No	Yes	No
	Create/Remove Service	Yes	No	No	Yes	No
	Create/Remove Repository	Yes	No	No	Yes	No
	Manage HA Sync	Yes	Yes	No	Yes	No
	Create PAR File	Yes	No	No	Yes	No
	Allow Config View on Box	Yes	Yes	Yes	Yes	No
	Allow Emergency Override	Yes	No	No	Yes	No
	Create/Remove Workspace	Yes	No	No	Yes	No
Change Workspaces	Yes	No	No	Yes	No	
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators

CC Control	Access to CC Control	Yes	Yes	Yes	Yes	Yes
	Show Map	Yes	Yes	Yes	Yes	Yes
	Show Config Updates	Yes	Yes	Yes	Yes	Yes
	Manage Config Updates	Yes	Yes	Yes	Yes	Yes
	Show Box REXEC	Yes	Yes	Yes	No	No
	Manage Box REXEC	Yes	Yes	No	No	No
	Show Box Firmware Updates	Yes	Yes	Yes	No	No
	Manage Box Firmware Updates	Yes	Yes	Yes	No	No
	Manage Box File Update	Yes	Yes	Yes	No	No
	Show Box File Update	Yes	Yes	Yes	No	No
	Manage Box Geo Position	Yes	Yes	Yes	Yes	No
	Manage Box Activation	Yes	Yes	No	Yes	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
CC Audit Info	Access to CC Audit Info	Yes	Yes	Yes	Yes	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
CC PKI	Access to CC PKI	Yes	No	Yes	Yes	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators

Control	Access to Control	Yes	Yes	Yes	Yes	No
	Start/Stop Server	Yes	Yes	No	No	No
	Block Server	Yes	Yes	No	No	No
	Start/Stop Service	Yes	Yes	No	No	No
	Block Service	Yes	Yes	No	No	No
	Delete Wild Route	Yes	Yes	No	No	No
	Activate New Configuration	Yes	Yes	Yes	Yes	No
	Restart Network Subsystem	Yes	Yes	No	No	No
	Set or Sync Box Time	Yes	Yes	Yes	Yes	No
	Firmware Restart	Yes	Yes	No	No	No
	Reboot/Shutdown System	Yes	Yes	No	No	No
	Activate Kernel Update	Yes	No	No	No	No
	Kill Sessions	Yes	Yes	No	No	No
	Import License	Yes	Yes	Yes	Yes	No
	Remove License	Yes	Yes	Yes	Yes	No
	View License Data	Yes	Yes	Yes	Yes	No
SCEP Operations	Yes	Yes	Yes	Yes	No	
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
Event	Access to Event	Yes	Yes	Yes	Yes	No
	Silence Events	Yes	Yes	No	Yes	No
	Stop Alarm	Yes	Yes	No	Yes	No
	Mark as Read	Yes	Yes	No	Yes	No
	Confirm Events	Yes	Yes	No	Yes	No
	Delete Events	Yes	No	No	Yes	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
Log	Access to Log	Yes	Yes	Yes	Yes	No
	Read Box Logfiles	Yes	Yes	Yes	Yes	No
	Delete Box Logfiles	Yes	No	No	Yes	No
	Read Service Logfiles	Yes	Yes	Yes	Yes	No
	Delete Service Logfiles	Yes	No	No	Yes	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators

Statistics	Access to Statistics	Yes	Yes	Yes	Yes	No
	Read Box Statistics	Yes	Yes	Yes	Yes	No
	Delete Box Statistics	Yes	No	No	Yes	No
	Read Service Statistics	Yes	Yes	Yes	Yes	No
	Delete Service Statistics	Yes	No	No	Yes	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
DHCP	Access to DHCP	Yes	Yes	Yes	No	No
	Enable Commands / deletion of lease	Yes	Yes	No	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
Access Control Service	Access to Access Control Service	Yes	Yes	Yes	No	No
	Enable Commands / deletion of access cache	Yes	No	No	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
CC Access Control Service	Access to CC Access Control Service	Yes	Yes	Yes	No	No
	Enable Commands	Yes	No	No	No	No
	Block Box Svnc	Yes	No	No	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
Firewall	Access to Firewall	Yes	Yes	Yes	Yes	No
	Terminate Connections	Yes	Yes	No	No	No
	Modify Connections	Yes	Yes	No	No	No
	Kill Handler Processes	Yes	Yes	No	No	No
	Dynamic Rule Control	Yes	Yes	No	No	No
	Toggle Trace	Yes	Yes	No	No	No
	View Trace Output	Yes	Yes	No	No	No
	Change Settings	Yes	Yes	No	No	No
	View Ruleset	Yes	Yes	Yes	Yes	No
	Manipulate Access Cache Entries	Yes	No	No	No	No
	Access ATD tab and Quarantine	Yes	No	No	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators

VPN	Access to VPN	Yes	Yes	Yes	Yes	No
	Terminate VPN Tunnels	Yes	Yes	No	No	No
	Disable/Enable VPN Tunnels	Yes	Yes	No	No	No
	View Configuration	Yes	Yes	Yes	Yes	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
Mail Router	Access to Mail Router	Yes	Yes	Yes	No	No
	Enable Commands	Yes	No	No	No	No
	View Stripped Attachments	Yes	No	No	No	No
	Retrieve Stripped Attachments	Yes	No	No	No	No
	Delete Stripped Attachments	Yes	No	No	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
Virus Scanner	Access to Virscan Service	Yes	Yes	Yes	No	No
	Allow Block Virus Pattern Update	Yes	Yes	No	No	No
	Allow Manual Virus Pattern Update	Yes	Yes	No	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
Secure Web Proxy	Access to Secure Web Proxy	Yes	Yes	Yes	No	No
	Access Cache Management	Yes	No	No	No	No
	Ticket Management	Yes	Yes	No	No	No
	Cert. Authorities Management	Yes	No	No	No	No
	XML Services Management	Yes	No	No	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
HTTP Proxy	Access to HTTP Proxy	Yes	Yes	Yes	No	No
Box Menu	Software Item	Manager	Operator	Observer	Editor	Administrators
WiFi	Access to WiFi	Yes	Yes	Yes	No	No

Configure Administrative Roles

1. Go to **CONFIGURATION > Configuration Tree > Multi-Range > Global Settings > Administrative Roles**.
2. Click **Lock**.
3. In the **Roles** section, click **+** to create a new role. You can also edit and modify an existing entry.
4. Enter a **Name** for the role (only numbers are allowed) and click **OK**. The **Roles** configuration window opens.
5. To provide the administrative role with access to a service,
 1. Select the **Access to** check box.
 2. Click **Set/Edit** to configure detailed permissions for the service and click **OK**.

It is recommended that you grant the **Show Map** permission in the **CC Control Module** section to every admin role. Admins that do not have this permission will get an error message immediately after they log into the Barracuda NG Control Center.
6. Click **OK**.
7. Click **Send Changes** and **Activate**.

You can now assign the administrative role to an administrative user profile (see [How to Configure Administrative Profiles](#)).

Apply the Administrative Role to a Profile

1. Click the **ADMINS** tab.
2. Right click the admin profile in the list and select **Lock**.
3. Edit the profile.
4. Select the administrative role from the **Roles** list. (If you just want to assign specific roles, clear the **Allow All Operations** check box.)
5. Click **OK**.
6. Click **Activate**.

The administrative user can now view and edit settings and services on the Barracuda NG Control Center according to their assigned roles.

© Barracuda Networks Inc., 2020 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.