
How to Remove a Barracuda Load Balancer ADC from a High Availability Environment

<https://campus.barracuda.com/doc/4532/>

Remove a System from a Cluster

A Barracuda Load Balancer ADC can be removed from the cluster at any time. Perform the following steps to remove a unit from the cluster:

1. On the **ADVANCED > High Availability** page of the Backup unit perform the following:
2. Clear the **Cluster Shared Secret** in the **Cluster Settings** section, and click **Save Changes**.
3. Click the delete icon under **Clustered Systems** to remove the other unit from the cluster.
4. On the **ADVANCED > High Availability** page of the Primary unit which is in cluster with this unit, click the delete icon under **Clustered Systems**.

Removing the unit from the cluster clears all configuration including Services from the Backup unit, and retains all configuration on the Primary unit.

Return a Unit to a Cluster

In case if you have removed the failed unit from the cluster and want to put it back in cluster, do the following:

1. Make sure the failed unit is removed from the network.
2. On the removed unit, navigate to the **ADVANCED > System Configuration** page and perform the **Clear Configuration** operation before putting the unit back into the network.

© Barracuda Networks Inc., 2025 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.