

How to Configure Repository Equivalence

<https://campus.barracuda.com/doc/46206947/>

This article refers to the Barracuda ArchiveOne version 6.5.1.2124 and higher.

To create a repository equivalence,

1. On the Archive server, browse to **\\Configuration_Server\Add-ins\AOnePol** where *Configuration_Server* is the name of the Configuration server where the Add-ins shared folder is hosted.

If you do not know the Configuration Server name, open the Admin console, and click the [Status Node](#).

2. Right-click in the folder, and click **New > Text Document**.
3. Rename the new text document: **AOneRepEquivalence.C2C**
4. Open the new file in Notepad, and then copy and paste the following into the file:

```
[RepEquivalence]
RepositoryEqMultiCountItem=1
[Original]
Name0=Original_Name
[Equivalence]
Name0=Current_Name
```

where **Original_Name** is the original name of the repository, and **Current_Name** is the existing name of the repository.

For example, you have a repository 2015 which you renamed to **2015Jan-June** then the configuration would be:

```
[RepEquivalence]
RepositoryEqMultiCountItem=1
[Original]
Name0=2015
[Equivalence]
Name0=2015Jan-June
```

For additional repositories, increment the **RepositoryEqMultiCountItem** value by one and the **Name** value by one as follows:

```
[RepEquivalence]
RepositoryEqMultiCountItem=3
[Original]
Name0=2015
Name1=2014
Name2=2013
[Equivalence]
Name0=Year_2015
```

Name1=Year_2014

Name2=Year_2013

5. Save and close the file.
6. Close and reopen the ArchiveOne Admin console to affect the configuration change.

© Barracuda Networks Inc., 2024 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.