

## How to Configure a RADIUS/EAP Server for Wi-Fi authentication

<https://campus.barracuda.com/doc/48203115/>

For large network environments, you can configure a RADIUS and EAP server to handle user authentication.

### Configure RADIUS/EAP Wi-Fi Authentication

1. Go to **CONFIGURATION > Configuration Tree > Box > Virtual Servers > your virtual server > Assigned Services > Wi-Fi > Wi-Fi AP Configuration**.
2. In the left menu, select **Radius/EAP**.
3. Click **Lock**.
4. In the **Primary RADIUS Server** section, you can edit the following settings for the primary RADIUS server:

Setting	Description
<b>NAS-IP Address</b>	The service IP address of the Wi-Fi access point.
<b>Other NAS-IP</b>	The alternative service IP address of the Wi-Fi access point.
<b>NAS-Identifier</b>	The NAS identifier string for RADIUS messages. For example, the fully qualified domain name.
<b>Authentication Server IP</b>	The IP address of the RADIUS authentication server.
<b>Authentication Port</b>	The port address of the RADIUS authentication server.
<b>Authentication Password</b>	The authentication password of the RADIUS authentication server.
<b>Use Accounting</b>	Enables RADIUS accounting.
<b>Accounting Server IP</b>	The IP address of the RADIUS accounting server.
<b>Accounting Port</b>	The IP port of the accounting server.
<b>Accounting Password</b>	The password of the accounting server.
<b>Accounting Update Interval[s]</b>	The time interval in seconds for obtaining accounting updates. You can enter 60 to 600 seconds.

5. In the **RADIUS Fallback Options** section, you can edit the following settings for a secondary or fallback RADIUS server:

Setting	Description
<b>Primary Retry Interval[s]</b>	The interval in seconds for trying to return to using the primary RADIUS server.
<b>Secondary Radius Servers</b>	The list of secondary or fallback RADIUS servers.

6. Click **Send Changes** and **Activate**.

© Barracuda Networks Inc., 2019 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.