

## How to Enable IPv6

<https://campus.barracuda.com/doc/49741986/>

By default, IPv6 is disabled on the F-Series Firewall. After enabling IPv6, you must activate the new network configuration and reboot the firewall.

### Step 1. Enable IPv6

1. Go to **CONFIGURATION > Configuration Tree > Box > Network**.
2. Click **Lock**.
3. In the **IP Version** section, select the **Enable IPv6** check box.



4. Click **Send Changes** and **Activate**.

### Step 2. Activate the network changes and reboot

1. Go to **CONTROL > Network** and activate the network changes.
2. In the left menu, click **Activate network configuration**.
3. Click **Failsafe**.
4. In the left menu, expand **Operating System** and click **Reboot Box**.

You can now configure and use IPv6 on your F-Series Firewall or Control Center.

## Figures

1. enable\_IPv6\_01.png

© Barracuda Networks Inc., 2019 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.