

## How to Activate and License a Stand-alone Hardware NextGen F-Series or Control Center Appliance

<https://campus.barracuda.com/doc/53248313/>

To automatically download and install the license on your NextGen Firewall F, connect to the firewall with NextGen Admin. NextGen Admin transmits the serial number of your unit to the Barracuda Licensing service and initiates the activation process. After completing the customer information form and accepting the EULA, your license is activated and automatically downloaded and installed on your unit.

### Before You Begin

- NextGen Admin must be able to connect to the Barracuda licensing servers.
- The firewall or Control Center hardware unit must be able to connect to the Barracuda licensing servers.
- (optional) NextGen Admin automatically uses the proxy address in the Windows registry. If a proxy is entered but disabled, NextGen Admin still uses it. You can enter a proxy in NextGen Admin by navigating to **OPTIONS > Settings > Barracuda Activation > Proxy Settings**.


### Automatically Download and Activate your Licenses

1. Log into the Barracuda NextGen Firewall F-Series using NextGen Admin.

**Default User:** root

**Default Password:** ngf1r3wall

2. (optional) Complete the Getting Started Wizard. For more information, see [Getting Started](#).
3. The activation process is initiated automatically after 30 seconds. You can also start the process manually by clicking on the blue arrow in the **Licensing** element on the **DASHBOARD**. After downloading the licenses, the activation form opens.



4. (**evaluation license only**) Click the **Evaluation License** check box.
5. Enter the **Customer** and **Purchase Information**.
6. Read/scroll through the terms and conditions and click the **I accept the Terms and Conditions** check box.

**Product Activation**

In order to complete activation of your product, please fill out the form below and press the "Activate" button.

Serial Number: BAR-XXXXXXXXXX  Is Eval License

<p><b>Customer Information</b></p> <p>First Name: <input type="text"/></p> <p>Last Name: <input type="text"/></p> <p>Company Name: <input type="text" value="Barracuda Networks Techlib"/></p> <p>Email: <input type="text"/></p> <p>Phone: <input type="text"/></p> <p>Country: <input type="text" value="AUSTRIA"/></p> <p>Street Address: <input type="text" value="Eduard Bodem Gasse 1"/></p> <p>City: <input type="text" value="Innsbruck"/></p> <p>State/Province: <input type="text" value="Tirol"/></p> <p>Zip/Postal Code: <input type="text" value="6020"/></p>	<p><b>Purchase Information</b></p> <p>Purchased From: <input type="text" value="Barracuda Networks"/></p> <p>Salesperson Name: <input type="text" value="Barracuda Networks"/></p> <p>Email: <input type="text" value="documentation@barracuda.com"/></p> <p>Phone: <input type="text" value="+43 508 100"/></p> <p>Country: <input type="text" value="AUSTRIA"/></p> <p>City: <input type="text" value="Innsbruck"/></p> <p>State/Province: <input type="text" value="Tirol"/></p> <p>Zip/Postal Code: <input type="text" value="6020"/></p>
--	---

**Accept the Agreement**

General

These terms are governed by the laws of the State of California, without respect to its conflict of law principles. Any action in connection with this site will be brought only in state or federal courts located in Santa Clara County, California, U.S.A., and both parties waive any objection to personal jurisdiction of and venue in such courts. Barracuda Networks makes no representations that the Content is appropriate or available for use in any manner and in particular outside the United States; and access from territories where the Content is illegal is prohibited. If you choose to access this site from outside the United States, you do so at your own initiative and you are responsible for complying with all local laws.

If any provision of these terms is unenforceable, the other terms will remain in full force and effect. Certain provisions of these terms may be superceded or extended by terms on specific pages of this site.

Revised: December 2012

I accept the Terms and Conditions

7. Click **Activate**. The activation process may take a couple of minutes.
  - o After the activation process, you will receive a notification email from Barracuda Networks Customer Services.
  - o If you are using a high availability setup, your secondary Barracuda NextGen Firewall F waits for the license to be activated and then receives the license from the primary unit.

<b>Uptime:</b>	4 Days and 23:08:12	<b>Firmware Version:</b>	GWAY-5.4.3-182
<b>System Time:</b>	Mon Jun 2 11:11:58 2014	<b>Appliance Model:</b>	
<b>Box:</b>	10.0.91.70 - doc	<b>Serial Number:</b>	010101
<b>License State:</b>	Normal box operation	<b>Number of CPUs:</b>	4
<b>Activation State:</b>	Current	<b>Architecture:</b>	64 bit
		<b>Admin Sessions:</b>	6

Your Barracuda appliance is now licensed and activated. Check **Control > Licenses** to see which licenses are installed on your unit.

## Normal box operation

### ACTIVE LICENSES

Name/Module	License	Expires	HostID	Status
<input checked="" type="checkbox"/> base-brf101	00000273-BN-F101-1410	01.01.2030 00:00:00	MAC-00:90:0b:15:3fa2	Valid-Host-ID
<input checked="" type="checkbox"/> add-brf101-e	00000273-BN-F101-EnergizeUpdate-1411	01.01.2030 00:00:00	MAC-00:90:0b:15:3fa2	Valid-Host-ID

### License Values

License: Barracuda  
 License-Model: F101  
 Demo Mode: no  
 Export Mode: no  
 CC managed: yes  
 Platform:  
 Product: f101  
 Configured Appliance: F101  
 Detected Appliance: F101  
 Serial Number: Z21446  
 Flash based: yes box config  
 Statistics: no flash  
 Licensed Tunnels: unlimited  
 Compression: licensed  
 Hardware Encryption: not-licensed  
 Padlock Encryption: licensed  
 VPN Shaping: licensed  
 NAC: not-licensed  
 Protected IPs: unlimited

## Figures

1. license\_activate\_element.png
2. activation\_form.png
3. license\_hw01.png
4. F101\_license.png

© Barracuda Networks Inc., 2020 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.