
Deleting Devices

<https://campus.barracuda.com/doc/90442826/>

This page provides the following topics:

- [To delete a device](#)
- [To delete a device manually on the Onboarding Overview page](#)
- [To delete devices with a down status automatically](#)

To delete a device

1. In Service Center, click **Status > Devices**.
2. Click a device name.
3. Click **Delete Device** on the right sidebar.

To delete a device manually on the Onboarding Overview page

1. In Service Center, click **Status > Onboarding Overview**.
2. Click the site that contains the device for which you want to turn monitoring off.
3. Select the check box that corresponds with the device you want to delete.
4. Click **More Actions > Delete**.

To delete devices with a down status automatically

You can modify the global interval for the removal of down devices.

Notes

- If an IP address belongs to a server device, it is not deleted automatically.
- If an IP address belongs to a workstation device and the device is down for more than the allotted down device setting, it is deleted on the next scan. For domain environments, if a device is a Standalone Workstation or a Member Workstation, it is considered a workstation. For workgroup environments, if a device is XP, Vista or Windows 7, it is considered a workstation.

Default

The default is 30 days for automatic removal.

1. In Service Center, click **Site Management > Sites**.
2. Click the name of the site that contains the device you want to delete.
3. Click the **Configuration** tab.
4. In the **Down Device Threshold Settings** section, click **Modify**.
5. Type the number of days a device must be consecutively down before it is automatically removed from the system.
6. Click **Save**.
7. Click **Close**.

© Barracuda Networks Inc., 2021 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.