

Adding a Monitor for Avast Antivirus

<https://campus.barracuda.com/doc/90443570/>

There are 5 monitors associated with Avast Antivirus in Barracuda Managed Workplace:

- **Avast Antivirus - Device Needs Restart**
- **Avast Antivirus - Protection Disabled**
- **Avast Antivirus - Threat Detected**
- **Avast Antivirus - Virus Definition Out-Of-Date**
- **Avast Antivirus - Virus Scan Overdue**

These monitors are also included in the Barracuda Managed Workplace Antivirus monitoring policy, which is used in conjunction with the **Antivirus** policies to monitor **Avast Antivirus** at your customer sites. If you choose to create your own monitoring policy for **Avast Antivirus**, you must add these monitors.

Prior to Barracuda Managed Workplace 12 SP1, the **Avast Antivirus - Virus Definition Out-Of-Date Monitor** alerted if the virus definition was out of date for 52 hours. Due to changes in the way **Avast** updates antivirus, this monitor now alerts if the virus definition is out of date for 7 days.

For more information on setting up **Avast Antivirus** monitoring, see [Setting up Avast Business Antivirus Monitoring](#).

1. In Service Center, click **Configuration > Monitor & Alert Rules**.
2. From the **Site** list, select the site where the device is located.
3. From the **Device** list, select the device to which you want to add a monitor.
4. Click **Add Monitor**.
5. Select one of the following monitors:
 - **Avast Antivirus - Device Needs Restart**
 - **Avast Antivirus - Protection Disabled**
 - **Avast Antivirus - Threat Detected**
 - **Avast Antivirus - Virus Definition Out-Of-Date**
 - **Avast Antivirus - Virus Scan Overdue**
6. Click **Add Monitor**.
7. In the **Monitor** tab, type a **title** for the monitor.
8. Optionally, type a **description** for the monitor.
9. To configure an alert, see [Setting Alert Actions](#).
10. Click **Save**.

© Barracuda Networks Inc., 2021 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.