

Access Controller Licensing

https://campus.barracuda.com/doc/96026748/

License and activate the Access Controller on the Firewall Control Center Licensing page. Secure Connector pool licenses are verified and enforced on the VPN server that handles the SC tunnel, assigning a single license to an Access Controller is optional. For general information about licensing, see <u>CloudGen Firewall Licensing</u>.

Step 1. License and Activate the Access Controller

License the Access Controller on the Control Center. The licenses are automatically downloaded and installed. For more information, see <u>How to Assign and Activate Single Licenses on a Control Center</u>.

Licenses			🥒 🕈 🛪 🗇 d
	License		Parameters
	autolic-0-	-bn-vac610-advan	mod=add-bnvac610-a id=M
	autolic-1-	-bn-vac610-energiz	mod=add-bnvac610-e id=M
	autolic-2-	-bn-vac610-malwar	mod=add-bnvac610-m id=N
	autolic-3-	-bn-vac610-14569	mod=base-bnvac610 id=M/
	<		

On your Access Controller, go to **CONTROL** > **Licenses** or **CONFIGURATION** > **Configuration Tree** > **Box** > **Licenses** to verify that the licenses are installed.

Step 2. Import the Secure Connector Pool License

Import and activate the Secure Connector Energize Updates (EU) pool license.

- 1. Log into the Control Center.
- 2. Go to **CONTROL > Licensing**.
- 3. Right-click in the **Pool Licenses** section and select **Import Pool License** from the context menu. The **Activate Pool License** window opens.

✓ POOL LICEN	ISES								
Activation State	Model		License ID	Instances	Usage		Available		Serial
Activated	VF25	Im	Import Pool License Use Unattended Activation			78762	10.05.2016	19.05.2021	2T3RF-U9XH8-{
Activated	VF2000					78763	27.08.2015	05.09.2020	4EEE4-4K1NK-5
Activated	VF2000	Use				34203	10.05.2016	19.05.2019	TP71N-1882Y-P
		Up	date Licenses on	CC					
		Ор	en Pool Licenses	Configuration					

4. Enter the Secure Connector Energize Updates license **Token**.



- 5. From the **Filter** list, select **All**.
- 6. From the **Product** list, select your Access Controller model: **VACC400**, **VACC610**, or **VACC820**.
- 7. Click **OK**.

Token	-	
Product	VACC610	×
Filter	All Appliance "F Virtual "VFxx Software "Sf	xx" (" =xx"
	ОК	Cancel

8. Fill in the **Activation Form**. Wait for the license to be activated and downloaded.

Step 3. (Optional) Assign the Secure Connector Pool License to the Access Controller

- 1. Go to your cluster > your Access Controller > Box Licenses.
- 2. Click Lock.
- 3. In the Licenses list, click + and select Import from Pool Licenses. The Select Pool Licenses window opens.
- 4. Clear the **Show only Licenses for VFxxx** check box.
- 5. Double-click the pool license you installed.

Select Pool License						
Show only Licenses for VF500						
License	Module	Model	Num	Used	Grace	SubModules
740552-BN-SC1-Pool-EnergizeUpdate-1456928014	add-bnsc		1	0	15	
<						>

6. Click Send Changes and Activate.

The Secure Connector EU pool license is now added to the Access Controller licenses.

License Configuration				
Licenses			💉 🕂 🗙 🕩 🗈	=
	License		Parameters	
	-bn-s	c1-pool-energizeupdate	Not yet issued	
	autolic-0-	-bn-vac610-advan	mod=add-bnvac610-a id=MAC	
	autolic-1-	-bn-vac610-energiz	mod=add-bnvac610-e id=MAC	;
	autolic-2-	-bn-vac610-malwar	mod=add-bnvac610-m id=MAC	
	autolic-3-	-bn-vac610-14569	mod=base-bnvac610 id=MAC-	
	<		>	

Barracuda CloudGen Firewall



Figures

- 1. deploy_SAC_01.png
- 2. deploy_SC_03.png
- 3. deploy_SC_04.png
- 4. deploy_sc04.png
- 5. deploy_sc05.png

© Barracuda Networks Inc., 2024 The information contained within this document is confidential and proprietary to Barracuda Networks Inc. No portion of this document may be copied, distributed, publicized or used for other than internal documentary purposes without the written consent of an official representative of Barracuda Networks Inc. All specifications are subject to change without notice. Barracuda Networks Inc. assumes no responsibility for any inaccuracies in this document. Barracuda Networks Inc. reserves the right to change, modify, transfer, or otherwise revise this publication without notice.